


### Applications

- High Frequency Synchronous Buck Converters for Computer Processor Power
- High Frequency Isolated DC-DC Converters with Synchronous Rectification for Telecom and Industrial Use

### Benefits

- Very Low RDS(on) at 4.5V V<sub>GS</sub>
- Ultra-Low Gate Impedance
- Fully Characterized Avalanche Voltage and Current

| V <sub>DSS</sub> | R <sub>DS(on)</sub> max | Q <sub>g</sub> |
|------------------|-------------------------|----------------|
| <b>30V</b>       | <b>3.3mΩ</b>            | <b>34nC</b>    |



### Absolute Maximum Ratings

|                                         | Parameter                                       | Max.             | Units |
|-----------------------------------------|-------------------------------------------------|------------------|-------|
| V <sub>DS</sub>                         | Drain-to-Source Voltage                         | 30               | V     |
| V <sub>GS</sub>                         | Gate-to-Source Voltage                          | ± 20             |       |
| I <sub>D</sub> @ T <sub>C</sub> = 25°C  | Continuous Drain Current, V <sub>GS</sub> @ 10V | 161 <sup>④</sup> | A     |
| I <sub>D</sub> @ T <sub>C</sub> = 100°C | Continuous Drain Current, V <sub>GS</sub> @ 10V | 113 <sup>④</sup> |       |
| I <sub>DM</sub>                         | Pulsed Drain Current <sup>①</sup>               | 620              |       |
| P <sub>D</sub> @ T <sub>C</sub> = 25°C  | Maximum Power Dissipation <sup>②</sup>          | 140              | W     |
| P <sub>D</sub> @ T <sub>C</sub> = 100°C | Maximum Power Dissipation <sup>②</sup>          | 71               |       |
|                                         | Linear Derating Factor                          | 0.95             | W/°C  |
| T <sub>J</sub>                          | Operating Junction and                          | -55 to + 175     | °C    |
| T <sub>STG</sub>                        | Storage Temperature Range                       |                  |       |
|                                         | Soldering Temperature, for 10 seconds           |                  |       |

### Thermal Resistance

|                  | Parameter                                    | Typ. | Max. | Units |
|------------------|----------------------------------------------|------|------|-------|
| R <sub>θJC</sub> | Junction-to-Case                             | —    | 1.05 | °C/W  |
| R <sub>θJA</sub> | Junction-to-Ambient (PCB Mount) <sup>③</sup> | —    | 50   |       |
| R <sub>θJA</sub> | Junction-to-Ambient                          | —    | 110  |       |

Notes <sup>①</sup> through <sup>③</sup> are on page 11

Static @  $T_J = 25^\circ\text{C}$  (unless otherwise specified)


|                                | Parameter                                  | Min. | Typ. | Max. | Units     | Conditions                                                               |
|--------------------------------|--------------------------------------------|------|------|------|-----------|--------------------------------------------------------------------------|
| $BV_{DSS}$                     | Drain-to-Source Breakdown Voltage          | 30   | —    | —    | V         | $V_{GS} = 0V, I_D = 250\mu A$                                            |
| $\Delta BV_{DSS}/\Delta T_J$   | Breakdown Voltage Temp. Coefficient        | —    | 19   | —    | mV/°C     | Reference to $25^\circ\text{C}$ , $I_D = 1mA$                            |
| $R_{DS(on)}$                   | Static Drain-to-Source On-Resistance       | —    | 2.6  | 3.3  | $m\Omega$ | $V_{GS} = 10V, I_D = 15A$ ③                                              |
|                                |                                            | —    | 3.2  | 4.0  |           | $V_{GS} = 4.5V, I_D = 12A$ ③                                             |
| $V_{GS(th)}$                   | Gate Threshold Voltage                     | 1.5  | —    | 2.3  | V         | $V_{DS} = V_{GS}, I_D = 250\mu A$                                        |
| $\Delta V_{GS(th)}/\Delta T_J$ | Gate Threshold Voltage Coefficient         | —    | -5.4 | —    | mV/°C     |                                                                          |
| $I_{DSS}$                      | Drain-to-Source Leakage Current            | —    | —    | 1.0  | $\mu A$   | $V_{DS} = 24V, V_{GS} = 0V$                                              |
|                                |                                            | —    | —    | 150  |           | $V_{DS} = 24V, V_{GS} = 0V, T_J = 125^\circ\text{C}$                     |
| $I_{GSS}$                      | Gate-to-Source Forward Leakage             | —    | —    | 100  | nA        | $V_{GS} = 20V$                                                           |
|                                | Gate-to-Source Reverse Leakage             | —    | —    | -100 |           | $V_{GS} = -20V$                                                          |
| $g_{fs}$                       | Forward Transconductance                   | 37   | —    | —    | S         | $V_{DS} = 15V, I_D = 12A$                                                |
| $Q_g$                          | Total Gate Charge                          | —    | 34   | 50   | nC        | $V_{DS} = 15V$<br>$V_{GS} = 4.5V$<br>$I_D = 12A$<br>See Fig. 16          |
| $Q_{gs1}$                      | Pre-V <sub>th</sub> Gate-to-Source Charge  | —    | 9.1  | —    |           |                                                                          |
| $Q_{gs2}$                      | Post-V <sub>th</sub> Gate-to-Source Charge | —    | 2.5  | —    |           |                                                                          |
| $Q_{gd}$                       | Gate-to-Drain Charge                       | —    | 12   | —    |           |                                                                          |
| $Q_{godr}$                     | Gate Charge Overdrive                      | —    | 10   | —    |           |                                                                          |
| $Q_{sw}$                       | Switch Charge ( $Q_{gs2} + Q_{gd}$ )       | —    | 15   | —    |           |                                                                          |
| $Q_{oss}$                      | Output Charge                              | —    | 21   | —    | nC        | $V_{DS} = 15V, V_{GS} = 0V$                                              |
| $t_{d(on)}$                    | Turn-On Delay Time                         | —    | 25   | —    | ns        | $V_{DD} = 15V, V_{GS} = 4.5V$ ③<br>$I_D = 12A$<br>Clamped Inductive Load |
| $t_r$                          | Rise Time                                  | —    | 42   | —    |           |                                                                          |
| $t_{d(off)}$                   | Turn-Off Delay Time                        | —    | 34   | —    |           |                                                                          |
| $t_f$                          | Fall Time                                  | —    | 19   | —    |           |                                                                          |
| $C_{iss}$                      | Input Capacitance                          | —    | 4380 | —    | pF        | $V_{GS} = 0V$                                                            |
| $C_{oss}$                      | Output Capacitance                         | —    | 940  | —    |           | $V_{DS} = 15V$                                                           |
| $C_{rss}$                      | Reverse Transfer Capacitance               | —    | 430  | —    |           | $f = 1.0MHz$                                                             |

## Avalanche Characteristics


|          | Parameter                       | Typ. | Max. | Units |
|----------|---------------------------------|------|------|-------|
| $E_{AS}$ | Single Pulse Avalanche Energy ② | —    | 1440 | mJ    |
| $I_{AR}$ | Avalanche Current ①             | —    | 12   | A     |
| $E_{AR}$ | Repetitive Avalanche Energy ①   | —    | 14   | mJ    |

## Diode Characteristics


|          | Parameter                                 | Min.                                                                 | Typ. | Max.  | Units | Conditions                                                              |
|----------|-------------------------------------------|----------------------------------------------------------------------|------|-------|-------|-------------------------------------------------------------------------|
| $I_S$    | Continuous Source Current<br>(Body Diode) | —                                                                    | —    | 161 ④ | A     | MOSFET symbol<br>showing the<br>integral reverse<br>p-n junction diode. |
| $I_{SM}$ | Pulsed Source Current<br>(Body Diode) ①   | —                                                                    | —    | 620   |       |                                                                         |
| $V_{SD}$ | Diode Forward Voltage                     | —                                                                    | —    | 1.0   | V     | $T_J = 25^\circ\text{C}, I_S = 12A, V_{GS} = 0V$ ③                      |
| $t_{rr}$ | Reverse Recovery Time                     | —                                                                    | 39   | 59    | ns    | $T_J = 25^\circ\text{C}, I_F = 12A, V_{DD} = 15V$                       |
| $Q_{rr}$ | Reverse Recovery Charge                   | —                                                                    | 36   | 54    | nC    | $di/dt = 100A/\mu s$ ③                                                  |
| $t_{on}$ | Forward Turn-On Time                      | Intrinsic turn-on time is negligible (turn-on is dominated by LS+LD) |      |       |       |                                                                         |




**Fig 1.** Typical Output Characteristics




**Fig 2.** Typical Output Characteristics




**Fig 3.** Typical Transfer Characteristics




**Fig 4.** Normalized On-Resistance vs. Temperature




**Fig 5.** Typical Capacitance vs. Drain-to-Source Voltage




**Fig 6.** Typical Gate Charge vs. Gate-to-Source Voltage




**Fig 7.** Typical Source-Drain Diode Forward Voltage




**Fig 8.** Maximum Safe Operating Area




**Fig 9.** Maximum Drain Current vs. Case Temperature



**Fig 10.** Threshold Voltage vs. Temperature




**Fig 11.** Maximum Effective Transient Thermal Impedance, Junction-to-Case




**Fig 12a.** Unclamped Inductive Test Circuit




**Fig 12b.** Unclamped Inductive Waveforms




**Fig 13.** Gate Charge Test Circuit




**Fig 12c.** Maximum Avalanche Energy Vs. Drain Current




**Fig 14a.** Switching Time Test Circuit



**Fig 14b.** Switching Time Waveforms



**Fig 15.** Peak Diode Recovery dv/dt Test Circuit for N-Channel HEXFET® Power MOSFETs



**Fig 16.** Gate Charge Waveform

## Power MOSFET Selection for Non-Isolated DC/DC Converters

### Control FET

Special attention has been given to the power losses in the switching elements of the circuit - Q1 and Q2. Power losses in the high side switch Q1, also called the Control FET, are impacted by the  $R_{ds(on)}$  of the MOSFET, but these conduction losses are only about one half of the total losses.

Power losses in the control switch Q1 are given by;

$$P_{loss} = P_{conduction} + P_{switching} + P_{drive} + P_{output}$$

This can be expanded and approximated by;

$$\begin{aligned} P_{loss} = & \left( I_{rms}^2 \times R_{ds(on)} \right) \\ & + \left( I \times \frac{Q_{gd}}{i_g} \times V_{in} \times f \right) + \left( I \times \frac{Q_{gs2}}{i_g} \times V_{in} \times f \right) \\ & + (Q_g \times V_g \times f) \\ & + \left( \frac{Q_{oss}}{2} \times V_{in} \times f \right) \end{aligned}$$

This simplified loss equation includes the terms  $Q_{gs2}$  and  $Q_{oss}$  which are new to Power MOSFET data sheets.

$Q_{gs2}$  is a sub element of traditional gate-source charge that is included in all MOSFET data sheets. The importance of splitting this gate-source charge into two sub elements,  $Q_{gs1}$  and  $Q_{gs2}$ , can be seen from Fig 16.

$Q_{gs2}$  indicates the charge that must be supplied by the gate driver between the time that the threshold voltage has been reached and the time the drain current rises to  $I_{dmax}$  at which time the drain voltage begins to change. Minimizing  $Q_{gs2}$  is a critical factor in reducing switching losses in Q1.

$Q_{oss}$  is the charge that must be supplied to the output capacitance of the MOSFET during every switching cycle. Figure A shows how  $Q_{oss}$  is formed by the parallel combination of the voltage dependant (non-linear) capacitance's  $C_{ds}$  and  $C_{dg}$  when multiplied by the power supply input buss voltage.

### Synchronous FET

The power loss equation for Q2 is approximated by;

$$\begin{aligned} P_{loss} = & P_{conduction} + P_{drive} + P_{output}^* \\ P_{loss} = & \left( I_{rms}^2 \times R_{ds(on)} \right) \\ & + (Q_g \times V_g \times f) \\ & + \left( \frac{Q_{oss}}{2} \times V_{in} \times f \right) + (Q_{rr} \times V_{in} \times f) \end{aligned}$$

\*dissipated primarily in Q1.

For the synchronous MOSFET Q2,  $R_{ds(on)}$  is an important characteristic; however, once again the importance of gate charge must not be overlooked since it impacts three critical areas. Under light load the MOSFET must still be turned on and off by the control IC so the gate drive losses become much more significant. Secondly, the output charge  $Q_{oss}$  and reverse recovery charge  $Q_{rr}$  both generate losses that are transferred to Q1 and increase the dissipation in that device. Thirdly, gate charge will impact the MOSFETs' susceptibility to Cdv/dt turn on.

The drain of Q2 is connected to the switching node of the converter and therefore sees transitions between ground and  $V_{in}$ . As Q1 turns on and off there is a rate of change of drain voltage dV/dt which is capacitively coupled to the gate of Q2 and can induce a voltage spike on the gate that is sufficient to turn the MOSFET on, resulting in shoot-through current. The ratio of  $Q_{gd}/Q_{gs1}$  must be minimized to reduce the potential for Cdv/dt turn on.





Figure A:  $Q_{oss}$  Characteristic

## D-Pak (TO-252AA) Package Outline


Dimensions are shown in millimeters (inches)



## D-Pak (TO-252AA) Part Marking Information


Notes: This part marking information applies to devices produced before 02/26/2001

EXAMPLE: THIS IS AN IRFR120  
WITH ASSEMBLY  
LOT CODE 9U1P



Notes: This part marking information applies to devices produced after 02/26/2001

EXAMPLE: THIS IS AN IRFR120  
WITH ASSEMBLY  
LOT CODE 1234  
ASSEMBLED ON WW 16, 1999  
IN THE ASSEMBLY LINE "A"



Dimensions are shown in millimeters (inches)

Technical drawing of a 3-pin connector. The drawing shows a top view and a side view. The top view is a rectangle with a central square area divided into three vertical sections labeled 1, 2, and 3. The side view shows the profile of the connector with a flat top and a rounded bottom. Dimensions are provided in inches and millimeters.

Dimensions (inches in parentheses):

- Overall width: 6.73 (.265)
- Width of section 1: 5.46 (.215)
- Width of section 2: 5.21 (.205)
- Width of section 3: 1.27 (.050)
- Width of section 4: 0.88 (.035)
- Height of section 1: 1.52 (.060)
- Height of section 2: 1.15 (.045)
- Height of section 3: 6.22 (.245)
- Height of section 4: 5.97 (.235)
- Height of section 5: 9.65 (.380)
- Height of section 6: 8.89 (.350)
- Height of section 7: 2.28 (.090)
- Height of section 8: 1.91 (.075)
- Height of section 9: 1.14 (.045)
- Height of section 10: 0.76 (.030)
- Height of section 11: 0.89 (.035)
- Height of section 12: 0.64 (.025)

Section labels: - A -, - B -

Section numbers: 1, 2, 3, 4

Section symbols: 3X, 2X

Section symbols: ⊕, ⊗, A, B

Section symbols: 0.25 (.010), M, A, B

Technical drawing of a mechanical part with dimensions and notes.

Dimensions (mm):

- 2.38 (.094)
- 2.19 (.086)
- 0.58 (.023)
- 0.46 (.018)
- 6.45 (.245)
- 5.68 (.224)
- 1.14 (.045)
- 0.89 (.035)
- 0.58 (.023)
- 0.46 (.018)

NOTES:

- 1 DIMEN
- 2 CONTI
- 3 CONF
- 4 DIMEN

SOLDE

1 - GATE  
2 - DRAIN  
3 - SOURCE  
4 - DRAIN


- 1 DIMENSIONING & TOLERANCING PER ANSI Y14.5M, 1982.
- 2 CONTROLLING DIMENSION : INCH.
- 3 CONFORMS TO JEDEC OUTLINE TO-252AA.
- 4 DIMENSIONS SHOWN ARE BEFORE SOLDER DIP,  
SOLDER DIP MAX. +0.16 (.006).

✓ DATE CODE  
YEAR = 0  
WEEK = 16


PART NUMBER  
DATE CODE  
YEAR 9 = 1999  
WEEK 19  
LINE A

## D-Pak (TO-252AA) Tape & Reel Information

Dimensions are shown in millimeters (inches)



- NOTES :
1. CONTROLLING DIMENSION : MILLIMETER.
  2. ALL DIMENSIONS ARE SHOWN IN MILLIMETERS ( INCHES ).
  3. OUTLINE CONFORMS TO EIA-481 & EIA-541.



- NOTES :
1. OUTLINE CONFORMS TO EIA-481.

### Notes:

- ① Repetitive rating; pulse width limited by max. junction temperature.
- ② Starting  $T_J = 25^\circ\text{C}$ ,  $L = 20\text{mH}$ ,  $R_G = 25\Omega$ ,  $I_{AS} = 12\text{A}$ .
- ③ Pulse width  $\leq 400\mu\text{s}$ ; duty cycle  $\leq 2\%$ .
- ④ Calculated continuous current based on maximum allowable junction temperature. Package limitation current is 30A.
- ⑤ When mounted on 1" square PCB (FR-4 or G-10 Material). For recommended footprint and soldering techniques refer to application note #AN-994.

Data and specifications subject to change without notice.  
This product has been designed and qualified for the Industrial market.  
Qualification Standards can be found on IR's Web site.