

Part Matrix vs. Code Matrix for Broadcast-based Applications

1. CS4931X/CS49330: BROADCAST APPLICATION SUBFAMILY

A Broadcast Application implies that data is either an Elementary Stream (ES) or Packetized Elementary Stream (PES) format.

Data delivery is either:

- Serial Bursty (Configure INPUTA3 and send data to the CDI port while monitoring CMPREQ throttle line to make sure that Input FIFO is not over/under-flowed.
- Parallel Bursty (Configure for INPUTA7 or INPUTA8 and send data to the parallel port in Motorola or Intel format).
- “PES over I²S” (Typically, data can not be delivered via an I²S or Left-Justified input, for any standard release broadcast-based application code, with the exception of AC3N, which accepts “PES over I²S” which follows a proprietary patent-pending packing technique developed by Cirrus Logic, Inc. This technique allows for the DSP to perform the Audio/Video Synchronization in the system. Most standard release application codes listed in this document can be modified accept “PES over I²S” upon request in addition to the signing of a CWLA.)

If compressed data is delivered to the DSP (via I²S or LJ) according to the IEC61937 specification, this would actually no longer be considered a “broadcast-based” application (with the exception of the AAST and AACT codes), regardless of the final product’s intended purpose.

If the data delivery is IEC61937-packed AC-3, MPEG Multichannel, MP3 or AAC, the designer should then refer to the “CS4932X/CS49330, Part Matrix vs. Code Matrix for AVR/Outboard Decoder-based Applications” as this would now be considered an AVR-based application in regards to the data delivery. This document is available from the Cirrus Logic website on the CS49300 Page.

All Broadcast-based applications follow these rules (except where noted):

Expected CLKIN = 27 MHz (Oscillator Value).

DSPCLK = Refer to AN162 (Sampling Frequency and Application Code Dependent).

Standard Hardware Configuration: OUTPUTA2 (DSP Masters MCLK, SCLK and LRCLK).

Refer to AN162 and its appendices for how to control Broadcast-based Standard Release Application Codes that run on the CS4931X and/or CS49330.

Part(ROMID)	AACE	AACP	AACT	AASE	AASP	AAST	AC3E	AC3N	AC3P	MP3E	MPSE	MPSP	PCMP	Minimum Licensing Required to Receive Sample/Production Quantities of IC
CS49310(2)	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Dolby Digital and AAC License (from Dolby Laboratories)
CS49311(2)	Y	Y	Y	Y	Y	Y				Y	Y	Y	Y	AAC License (from Dolby Laboratories)
CS49312(2)							Y	Y	Y	Y	Y	Y	Y	Dolby Digital License (from Dolby Laboratories)
CS49330(2)										Y	Y	Y	Y	General-Purpose Part

Table 1. CS4931X/CS49330: Broadcast Application Subfamily & Associated Broadcast-Based Application Codes

The designer/manufacture should be aware that obtaining and/or evaluation of any/all application codes requires signing of a Crystal Ware Software Licensing Agreement (CWSEA). A Crystal Ware Licensing Agreement (CWLA) must be signed

before any/all application codes may be used in any production-level design. Please contact your Cirrus Logic Sales Representative or FAE in order to obtain the necessary contracts, application codes and application notes.

Code Name	Required Licensing	Documentation	Supported Input Data Type	Data Delivery Technique	IEC61937 Output	IEC60958 Output	External SRAM Required
AACE	Dolby	AN162	AAC, ES	Serial/Parallel Bursty	No	Yes	Yes - 32K x 8, 70ns
AACP	Dolby	AN162	AAC, PES	Serial/Parallel Bursty	No	Yes	Yes - 32K x 8, 70ns
AACT	Dolby	AN162C	AAC, IEC61937	I ² S, LJ	No	Yes	Yes - 32K x 8, 70ns
AASE	Dolby	AN162	AAC, ES	Serial/Parallel Bursty	Yes	Yes	No
AASP	Dolby	AN162	AAC, PES	Serial/Parallel Bursty	Yes	Yes	No
AAST	Dolby	AN162C	AAC, IEC61937	I ² S, LJ	Yes	Yes	No
AC3E	Dolby	AN162	AC3, ES	Serial/Parallel Bursty	Yes	Yes	No
AC3N	Dolby	AN162B	AC3, "PES over I ² S"	"PES over I ² S or LJ"	Yes	Yes	No
AC3P	Dolby	AN162	AC3, PES	Serial/Parallel Bursty	Yes	Yes	No
MP3E	None	AN162	MP3, ES	Serial/Parallel Bursty	Yes	Yes	No
MPSE	None	AN162	MPEG, ES	Serial/Parallel Bursty	No	Yes	No
MPSP	None	AN162	MPEG, PES	Serial/Parallel Bursty	No	Yes	No
PCMP	None	AN162A	SMPTE302M	Serial/Parallel Bursty	No	Yes	No
PCMP	None	AN162A	PCM	I ² S, LJ	No	Yes	No

Table 2. CS4931X/CS49330 Broadcast-based Application Codes

Contacting Cirrus Logic Support

For a complete listing of Direct Sales, Distributor, and Sales Representative contacts, visit the Cirrus Logic web site at:

<http://www.cirrus.com/corporate/contacts/>

Dolby Digital, AC-3, Dolby Pro Logic, Dolby Pro Logic II, Dolby Surround, Surround EX, Virtual Dolby Digital and the "AAC" logo are trademarks and the "Dolby Digital" logo, "Dolby Digital with Pro Logic II" logo, "Dolby" and the double-"D" symbol are registered trademarks of Dolby Laboratories Licensing Corporation. DTS, DTS Digital Surround, DTS-ES Extended Surround, DTS Neo:6, and DTS Virtual 5.1 are trademarks and the "DTS", "DTS-ES", "DTS Virtual 5.1" logos are registered trademarks of the Digital Theater Systems Corporation. The "MPEG Logo" is a registered trademark of Philips Electronics N.V. Home THX Cinema and THX are registered trademarks of Lucasfilm Ltd. Surround EX is a jointly developed technology of THX and Dolby Labs, Inc. AAC (Advanced Audio Coding) is an "MPEG-2-standard-based" digital audio compression algorithm (offering up to 5.1 discrete decoded channels for this implementation) collaboratively developed by AT&T, the Fraunhofer Institute, Dolby Laboratories, and the Sony Corporation. In regards to the MP3 capable functionality of the CS49300 Family DSP (via downloading of mp3_493xxx_vv.ld and mp3e_493xxx_vv.ld application codes) the following statements are applicable: "Supply of this product conveys a license for personal, private and non-commercial use. MPEG Layer-3 audio decoding technology licensed from Fraunhofer IIS and THOMSON Multimedia." MLP and Meridian Lossless Packing are registered trademarks of Meridian Audio Ltd. Harman VMAx is a registered trademark of Harman International. The Logic 7 logo and Logic 7 are registered trademarks of Lexicon. SRS CircleSurround, and SRS TruSurround are trademarks of SRS Labs, Inc. The HDCD logo, HDCD, High Definition Compatible Digital and Pacific Microsonics are either registered trademarks or trademarks of Pacific Microsonics, Inc. in the United States and/or other countries. HDCD technology provided under license from Pacific Microsonics, Inc. This product's software is covered by one or more of the following in the United States: 5,479,168; 5,638,074; 5,640,161; 5,872,531; 5,808,574; 5,838,274; 5,854,600; 5,864,311; and in Australia: 669114; with other patents pending. Intel is a registered trademark of Intel Corporation. Motorola is a registered trademark of Motorola, Inc. I²C is a registered trademark of Philips Semiconductor. Purchase of I²C Components of Cirrus Logic, Inc., or one of its sublicensed Associated Companies conveys a license under the Philips I²C Patent Rights to use those components in a standard I²C system. The "Crystal Logo" and the "Crystal Digital Sound Processing Logo" are registered trademarks of Cirrus Logic, Inc. All other names are trademarks, registered trademarks, or service marks of their respective companies.

Preliminary product information describes products which are in production, but for which full characterization data is not yet available. Advance product information describes products which are in development and subject to development changes. Cirrus Logic, Inc. has made best efforts to ensure that the information contained in this document is accurate and reliable. However, the information is subject to change without notice and is provided "AS IS" without warranty of any kind (express or implied). No responsibility is assumed by Cirrus Logic, Inc. for the use of this information, nor for infringements of patents or other rights of third parties. This document is the property of Cirrus Logic, Inc. and implies no license under patents, copyrights, trademarks, or trade secrets. No part of this publication may be copied, reproduced, stored in a retrieval system, or transmitted, in any form or by any means (electronic, mechanical, photographic, or otherwise) without the prior written consent of Cirrus Logic, Inc. Items from any Cirrus Logic website or disk may be printed for use by the user. However, no part of the printout or electronic files may be copied, reproduced, stored in a retrieval system, or transmitted, in any form or by any means (electronic, mechanical, photographic, or otherwise) without the prior written consent of Cirrus Logic, Inc. The names of products of Cirrus Logic, Inc. or other vendors and suppliers appearing in this document may be trademarks or service marks of their respective owners which may be registered in some jurisdictions. A list of Cirrus Logic, Inc. trademarks and service marks can be found at <http://www.cirrus.com>.

2. BROADCAST-BASED STANDARD RELEASE APPLICATION CODES

2.1 Application Code Name, Description, Notes and Associated Logo

- **AACE** - Multichannel MPEG-2 AAC decoder supporting elementary AAC, (LC, ADTS) input with up to a 5.1 channel discrete output. Additionally, an IEC60958 Lt, Rt output is supported from the AUDAT3/XMT958 pin. External SRAM is required for this application code.



- **AACP** - Multichannel MPEG-2 AAC decoder supporting PES parsing and AV Sync for PES packed AAC (LC, ADTS) input with up to 5.1 channel discrete output. Additionally, an IEC60958 Lt, Rt output is supported from the AUDAT3/XMT958 pin. External SRAM is required for this application code.



- **AACT** - Multichannel MPEG-2 AAC decoder supporting IEC61937-packed AAC (LC, ADTS) input with up to 5.1 channel discrete output. While this code normally would be considered AVR-based application code, it expects a 27MHz Oscillator on CLKIN and was developed specifically for a TeraLogic reference design. PCM mixing via the DAI input port is available for sources that have an input that has a matched Fs (32kHz, 44.1kHz or 48kHz) to that of the decoded AAC stream. This code has a default of OUTPUTA0, where all other Broadcast-based codes default to OUTPUTA2. Additionally, an IEC60958 Lt, Rt output is supported from the AUDAT3/XMT958 pin. External SRAM is

required for this application code.



- **AASE** - Multichannel MPEG-2 AAC decoder supporting elementary AAC, (LC, ADTS) input with a 2-channel downmixed output. PCM mixing of a 12kHz mono stream, via the DAI input port, is available when the decoded AAC stream has an Fs of 48kHz. Beep and Tone Generation is also supported. Additionally, an IEC60958 Lt, Rt output or an IEC61937 compressed output is supported from the AUDAT3/XMT958 pin. External SRAM is NOT required for this application code.



- **AASP** - Multichannel MPEG-2 AAC decoder supporting PES parsing and AV Sync for PES packed AAC (LC, ADTS) input with a 2-channel downmixed output. PCM mixing of a 12kHz mono stream, via the DAI input port, is available when the decoded AAC stream has an Fs of 48kHz. Beep and Tone Generation is also supported. Additionally, an IEC60958 Lt, Rt output or an IEC61937 compressed output is supported from the AUDAT3/XMT958 pin. External SRAM is NOT required for this application code.



- **AAST** - Multichannel MPEG-2 AAC decoder supporting IEC61937-packed AAC (LC, ADTS) input with a 2-channel downmixed output. While this code normally would be considered AVR-based application code, it expects a 27MHz Oscillator on CLKIN and was developed specifically for a TeraLogic reference design. PCM mixing via the DAI

input port is available for sources that have an input that has a matched Fs (32kHz, 44.1kHz or 48kHz) to that of the decoded AAC stream. This code has a default of OUTPUTA0, where all other Broadcast-based codes default to OUTPUTA2. Additionally, an IEC60958 Lt, Rt output or an IEC61937 compressed output is supported from the AUDAT3/XMT958 pin. External SRAM is NOT required for this application code.



- AC3E - Dolby Digital™ decoder supporting elementary stream input. Additionally, an IEC60958 Lt, Rt output is supported from the AUDAT3/XMT958 pin.



- AC3N - Dolby Digital decoder supporting PES parsing and AV Sync for data that is delivered according to the “PES over I²S” Cirrus Logic proprietary packing technique. Additionally, an IEC60958 Lt, Rt output or IEC61937 compressed output is supported from the AUDAT3/XMT958 pin.



- AC3P - Dolby Digital decoder supporting PES parsing and AV Sync. Additionally, an IEC60958 Lt, Rt output or IEC61937 compressed output is supported from the AUDAT3/XMT958 pin.



- MP3E - MP3 decoder supporting elementary stream input. Supports MPEG-1, Layer 3 as well as MPEG-2, Layer 3 streams (which includes support for Low Sampling Rate streams). Additionally, an IEC60958 stereo

output (Decoded MP3 audio in PCM format) or an IEC61937 compressed output is supported from the AUDAT3/XMT958 pin. (Please refer to the legal section for more information about the use of this application code).

- MPSE - MPEG stereo decoder supporting elementary MPEG stereo input with a 2-channel output. Supports MPEG-1, Layers 1 and 2; MPEG-2, Layer 2. MPEG-2 Low Sampling Rates not supported. Additionally, an IEC60958 stereo output is supported from the AUDAT3/XMT958 pin.



- MPSP - MPEG stereo decoder supporting PES parsing and AV Sync for PES-packed MPEG stereo input with a 2-channel output. Supports MPEG-1, Layers 1 and 2; MPEG-2, Layer 2. MPEG-2 Low Sampling Rates not supported. Additionally, an IEC60958 stereo output is supported from the AUDAT3/XMT958 pin.



- PCMP - The PCMP application code is a SMPTE 302M decoder designed for broadcast applications where PCM is delivered in an MPEG2 transport stream PES packet. It provides support for AV synchronization, channel change, bitstream parameter reporting and PLL control, among other features offered in other broadcast-based application codes discussed in AN162.

In addition, a mutually exclusive PCM pass-through application mode is available with the PCMP releases. This is similar to the AVR-based AC-3 code that is capable of passing PCM via I²S data delivery.



• Notes •

SMART
Analog™