

**SPECIFICATION SHEET**  
**JFW MODEL 50P-1633**  
**RELAY PROGRAMMABLE ATTENUATOR**

JFW Industries, Inc.  
 Phone: 317-887-1340  
 sales@jfwindustries.com  
 www.jfwindustries.com

Frequency Range	DC-1000 MHz
Impedance	50 Ohms nominal
Attenuation Range	0-64.5 dB in 0.1 dB steps
Attenuation Steps	0.1, 0.2, 0.4, 0.8, 1, 2, 4, 8, 16, and 32 dB
VSWR	1.4:1 maximum
Attenuation Accuracy	0.1, 0.2, 0.4, 0.8 dB ± 0.05 dB 1, 2 dB ± 0.07 dB 4 dB ± 0.1 dB 8 dB ± 0.15 dB 16, 32 dB ± 0.25 dB Accumulated Error ± 0.25 dB or 2%
Insertion Loss	4 dB nominal
RF Input Power	0.5 Watts average
Switching Speed	6 milliseconds
DC Supply / Control	+12 Vdc @ 30 mA per relay
DC Connector	Solder terminals
RF Connector	SMA, BNC, TNC, or N female
Physical Size	See outline drawing 092-4448

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	04/05/2004		TRS 04/05/2004				
14364	07/06/2007	A	TRS 07/06/2007				