

# P-CHANNEL JFETs



**TO-92/TO-226AA**

## ELECTRICAL CHARACTERISTICS at $T_A = 25^\circ\text{C}$

Device Type	$V_{(BR)GSS}$		$I_{GSS}$		$V_{GS(off)}$				$I_{DSS}$			$g_{fs}$			$C_{rss}^1$		$C_{rss}^1$		$r_{DS}$	Pin-ning 1, 2, 3
					Limits		Conditions													
	Min.	@ $I_G$	Max.	@ $V_{DS}$	Min.	Max.	$V_{DS}$	$I_D$	Min.	Max.	@ $V_{DS}$	Min.	Max.	@ $V_{DS}$	Max.	@ $V_{DS}$	Max.	@ $V_{DS}$	Max.	
(V)	( $\mu\text{A}$ )	(nA)	(V)	(V)	(V)	(nA)	(mA)	(mA)	(V)	(mS)	(mS)	(V)	(pF)	(V)	(pF)	(V)	( $\Omega$ )			
2N3920	20	10	20	10	—	8.0	-10	$-10^2$	-0.3	-15	-10	0.8	5.0	-10	32	-10	16	-10	—	DGS†
TP3993	25	1.0	1.0	15	4.0	9.5	-10	$-1^2$	-10	—	-10	6.0	12	-10	16	-10	$5.5 \cdot 10^3$	150	—	DSG‡
TP3994	25	1.0	1.0	15	1.0	5.5	-10	$-1^2$	-2.0	—	-10	4.0	10	-10	16	-10	$5.5 \cdot 10^3$	300	—	DSG‡
TP4381	25	1.0	1.0	15	1.0	5.0	-15	$-1.0^2$	-3.0	-12	-15	2.0	6.0	-15	20	-15	$5.0 \cdot 10^3$	—	—	DSG‡
2N5460	40	10	5.0	20	0.75	6.0	-15	-1.0	-1.0	-5.0	-15	1.0	5.0	-15	7.0	-15	3.0	-15	—	DSG‡
2N5461	40	10	5.0	20	1.0	7.5	-15	-1.0	-2.0	-9.0	-15	1.5	5.5	-15	7.0	-15	3.0	-15	—	DSG‡
2N5462	40	10	5.0	20	1.8	9.0	-15	-1.0	-4.0	-16	-15	2.0	6.0	-15	7.0	-15	3.0	-15	—	DSG‡
J174	30	1.0	1.0	20	5.0	10	-15	-10	-20	-135	-15	—	—	—	—	—	—	—	85	DSG†
J175	30	1.0	1.0	20	3.0	6.0	-15	-10	-7.0	-70	-15	—	—	—	—	—	—	—	125	DSG†
J176	30	1.0	1.0	20	1.0	4.0	-15	-10	-2.0	-35	-15	—	—	—	—	—	—	—	250	DSG†
J177	30	1.0	1.0	20	0.8	2.25	-15	10	-1.5	-20	-15	—	—	—	—	—	—	—	300	DSG†
TPU304	30	1.0	1.0	20	5.0	10	-15	$-1^2$	-30	-90	-15	—	—	—	27	-15	$7.0 \cdot 10^3$	85	—	DSG‡
TPU305	30	1.0	1.0	20	3.0	6.0	-15	$-1^2$	-15	-60	-15	—	—	—	27	-15	$7.0 \cdot 10^3$	110	—	DSG‡
TPU306	30	1.0	1.0	20	1.0	4.0	-15	$-1^2$	-5.0	-25	-15	—	—	—	27	-15	$7 \cdot 5.0^3$	175	—	DSG‡

NOTES: † Reversed pinning (S-G-D) available on special order—add suffix letter 'R' to part number.

‡ Reversed pinning (S-D-G) available on special order—add suffix letter 'R' to part number.

- 1)  $V_{GS} = 0 \text{ V}$ .
- 2)  $I_D$  in  $\mu\text{A}$ .
- 3)  $V_{DS} = 0 \text{ V}$ ,  $V_{GS}$  in volts.
- 4)  $V_{GS} = 1.0 \text{ V}$ .