

Philips Components

Data sheet	
status	Preliminary specification
date of issue	March 1991

BUK451-60A/B

PowerMOS transistor

PHILIPS INTERNATIONAL

56E D ■ 7110826 0044569 298 ■ PHIN

GENERAL DESCRIPTION

N-channel enhancement mode field-effect power transistor in a plastic envelope.
 The device is intended for use in Switched Mode Power Supplies (SMPS), motor control, welding, DC/DC and AC/DC converters, and in automotive and general purpose switching applications.


PINNING - TO220AB

PIN	DESCRIPTION
1	gate
2	drain
3	source
tab	drain


QUICK REFERENCE DATA

SYMBOL	PARAMETER	MAX.	MAX.	UNIT
V_{DS}	BUK451	-60A	-60B	V
I_D	Drain-source voltage	60	60	
P_{tot}	Drain current (DC)	5.0	5.0	A
T_J	Total power dissipation	40	40	W
$R_{DS(on)}$	Junction temperature	175	175	°C
	Drain-source on-state resistance	0.4	0.5	Ω

PIN CONFIGURATION



SYMBOL



LIMITING VALUES

Limiting values in accordance with the Absolute Maximum System (IEC 134)

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.		UNIT
V_{DS} V_{DGR} $\pm V_{GS}$	Drain-source voltage	-	-	60		V
	Drain-gate voltage	$R_{GS} = 20 \text{ k}\Omega$	-	60		V
	Gate-source voltage	-	-	30		V
I_D I_D I_{DM}	Drain current (DC)	$T_{mb} = 25^\circ\text{C}$	-	-60A	-60B	A
	Drain current (DC)	$T_{mb} = 100^\circ\text{C}$	-	5.0	5.0	A
	Drain current (pulse peak value)	$T_{mb} = 25^\circ\text{C}$	-	20	4.8	A
P_{tot} T_{stg} T_J	Total power dissipation	$T_{mb} = 25^\circ\text{C}$	-	40		W
	Storage temperature	-	-55	175		°C
	Junction Temperature	-	-	175		°C

PowerMOS transistor**BUK451-60A/B**

PHILIPS INTERNATIONAL
THERMAL RESISTANCES

From junction to mounting base	$R_{th,j-mb} = 3.75 \text{ K/W}$
From junction to ambient	$R_{th,j-a} = 60 \text{ K/W}$

STATIC CHARACTERISTICS $T_{mb} = 25^\circ\text{C}$ unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
$V_{(BR)DSS}$	Drain-source breakdown voltage	$V_{GS} = 0 \text{ V}; I_D = 0.25 \text{ mA}$	60	-	-	V
$V_{GS(TO)}$	Gate threshold voltage	$V_{DS} = V_{GS}; I_D = 1 \text{ mA}$	2.1	3.0	4.0	V
I_{DSS}	Zero gate voltage drain current	$V_{DS} = 60 \text{ V}; V_{GS} = 0 \text{ V}; T_j = 25^\circ\text{C}$	-	1	10	μA
I_{DS}	Zero gate voltage drain current	$V_{DS} = 60 \text{ V}; V_{GS} = 0 \text{ V}; T_j = 125^\circ\text{C}$	-	0.1	1.0	mA
I_{GSS}	Gate source leakage current	$V_{GS} = \pm 30 \text{ V}; V_{DS} = 0 \text{ V}$	-	10	100	nA
$R_{DS(ON)}$	Drain-source on-state resistance	$V_{GS} = 10 \text{ V}; V_{DS} = 0 \text{ V}$ $I_D = 4.0 \text{ A}$	BUK451-60A BUK451-60B	0.25 0.40	0.4 0.5	Ω

DYNAMIC CHARACTERISTICS $T_{mb} = 25^\circ\text{C}$ unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
g_{fs}	Forward transconductance	$V_{DS} = 25 \text{ V}; I_D = 4.0 \text{ A}$	1.5	1.9	-	S
C_{iss}	Input capacitance	$V_{GS} = 0 \text{ V}; V_{DS} = 25 \text{ V}; f = 1 \text{ MHz}$	-	160	240	pF
C_{oss}	Output capacitance		-	75	100	pF
C_{rss}	Feedback capacitance		-	35	50	pF
$t_{d(on)}$	Turn-on delay time	$V_{DD} = 30 \text{ V}; I_D = 3 \text{ A}; V_{GS} = 10 \text{ V}; R_{GS} = 50 \Omega; R_{gen} = 50 \Omega$	-	4	6	ns
$t_{r(on)}$	Turn-on rise time		-	15	25	ns
$t_{d(off)}$	Turn-off delay time		-	10	20	ns
t_f	Turn-off fall time		-	15	25	ns
L_d	Internal drain inductance	Measured from contact screw on tab to centre of die	-	3.5	-	nH
L_d	Internal drain inductance	Measured from drain lead 6 mm from package to centre of die	-	4.5	-	nH
L_s	Internal source inductance	Measured from source lead 6 mm from package to source bond pad	-	7.5	-	nH

REVERSE DIODE LIMITING VALUES AND CHARACTERISTICS $T_{mb} = 25^\circ\text{C}$ unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
I_{DR}	Continuous reverse drain current	-	-	-	5.0	A
I_{DRM}	Pulsed reverse drain current	-	-	-	20	A
V_{SD}	Diode forward voltage	$I_F = 5.0 \text{ A}; V_{GS} = 0 \text{ V}$	-	1.1	1.5	V
t_{rr}	Reverse recovery time	$I_F = 5.0 \text{ A}; -dI_F/dt = 100 \text{ A}/\mu\text{s}; V_{GS} = 0 \text{ V}; V_R = 30 \text{ V}$	-	60	-	ns
Q_{rr}	Reverse recovery charge		-	0.15	-	μC

PowerMOS transistor

PHILIPS INTERNATIONAL

56E D

BUK451-60A/B

■ 7110826 0044571 946 ■ PHIN




Fig. 1. Normalised power dissipation.
 $PD\% = 100 \cdot P_D / P_{D, 25^\circ C} = f(T_{mb})$




Fig. 4. Transient thermal impedance.
 $Z_{th(j-mb)} = f(t); \text{parameter } D = t_p/T$




Fig. 2. Normalised continuous drain current.
 $ID\% = 100 \cdot I_D / I_{D, 25^\circ C} = f(T_{mb}); \text{conditions: } V_{GS} \geq 5 \text{ V}$




Fig. 5. Typical output characteristics, $T_i = 25^\circ C$.
 $I_D = f(V_{DS}); \text{parameter } V_{GS}$




Fig. 3. Safe operating area, $T_{mb} = 25^\circ C$
 $I_D \& I_{DM} = f(V_{DS}); I_{DM} \text{ single pulse; parameter } t_p$




Fig. 6. Typical on-state resistance, $T_i = 25^\circ C$.
 $R_{DS(ON)} = f(I_D); \text{parameter } V_{GS}$

PowerMOS transistor**BUK451-60A/B****PHILIPS INTERNATIONAL**

56E D ■ 7110826 0044572 882 ■ PHIN




Fig. 7. Typical transfer characteristics.
 $I_D = f(V_{GS})$; conditions: $V_{DS} = 25 \text{ V}$; parameter T_j




Fig. 10. Gate threshold voltage.
 $V_{GS(TO)} = f(T_j)$; conditions: $I_D = 1 \text{ mA}$; $V_{DS} = V_{GS}$




Fig. 8. Typical transconductance, $T_j = 25^\circ\text{C}$.
 $g_{fs} = f(I_D)$; conditions: $V_{DS} = 25 \text{ V}$




Fig. 11. Sub-threshold drain current.
 $I_D = f(V_{GS})$; conditions: $T_j = 25^\circ\text{C}$; $V_{DS} = V_{GS}$




Fig. 9. Normalised drain-source on-state resistance.
 $a = R_{DS(ON)}/R_{DS(ON)25^\circ\text{C}} = f(T_j)$; $I_D = 4.0 \text{ A}$; $V_{GS} = 5 \text{ V}$




Fig. 12. Typical capacitances, C_{iss} , C_{oss} , C_{rss} .
 $C = f(V_{DS})$; conditions: $V_{GS} = 0 \text{ V}$; $f = 1 \text{ MHz}$

PowerMOS transistor

PHILIPS INTERNATIONAL

56E D

BUK451-60A/B

■ 7110826 0044573 719 ■ PHIN




Fig.13. Typical turn-on gate-charge characteristics.
 $V_{GS} = f(Q_G)$; conditions: $I_D = 5 \text{ A}$; parameter V_{DS}




Fig.14. Typical reverse diode current.
 $I_F = f(V_{DS})$; conditions: $V_{GS} = 0 \text{ V}$; parameter T_J