

# MN188321


## ■ Outline

The MN188321 has the same functions as those of the MN18881, except that capacities of the built-in ROM and RAM of the MN18881 are increased.

## ■ Features

- ROM capacity: 32,768 × 8bits
- RAM capacity: 448 × 8bits  
(data area and stack area)
- Interrupt: External interrupt 2  
 Timer interrupt 3  
 Serial interrupt 2  
 Abnormal run detect interrupt 1
- Timer/counter: 16-bit programmable timer × 4  
 Timer function  
 Event count function  
 Baud rate generator  
 16-bit binary counter × 1  
 Time base function  
 Watchdog function
- Serial interface: 8-bit sync.type  
 1 channel  
 Start condition addable  
 8-bit start-stop sync.type  
 1 channel
- ROM, RAM external extension:  
 Both ROM and RAM extendible up to 64 KB
- I/O pins: Memory mapped I/O system  
 8 for per-bit direction control I/O port  
 (3 of them combined with serial interface)  
 40 for per-byte direction control I/O port  
 8 for input port (various function combined)
- Package: 64-QFP/64-SDIP
- Piggyback: EP188321

## ■ Pin Configuration



## ■ Pin Descriptions

Symbol	Pin	I/O	Description
V <sub>DD</sub>	Power supply	—	Connect +5V.
V <sub>SS</sub>	Power supply	—	Connect 0V(GND).
OSC1	Oscillation input	I	High-speed system clock oscillation input pin
OSC2	Oscillation output	O	High-speed system clock oscillation output pin
XI/IRQ0/P24	Oscillation input	I	Low-speed system clock oscillation input pin. Also available as an IRQ0(interrupt) input pin or an input port.
XO	Oscillation output	O	Low-speed system clock oscillation output pin.
RST	Reset	I	Pin to reset the microcomputer
EXI	Operation mode	I	Pins to set the extension mode. System clock S2 is outputted from EXO.
EXO	selector	O	
TXD (P00)	UART data send	O (I)	Start-stop sync. serial interface(UART) serial data output pin. Also available as an input port.
RXD (P01)	UART data receive	I	Start-stop sync. serial interface(UART) serial data input pin. Also available as an input port.
SBT (P15)	Sync. serial clock I/O	I/O	Sync. serial interface clock I/O pin. Also available as an I/O port.
SBI (P16)	Sync. serial data input	I (I/O)	Sync. serial interface data input pin. Also available as an I/O port.
SBO (P17)	Sync. serial data output	I (I/O)	Sync. serial interface data output pin. Also available as an I/O port.
TCIO0~1 (P20~P21)	Timer/event counter I/O	I/O (I)	Timer/event counter I/O pins. Also available as input ports.
IRQ1~2 (P25~P26)	External interrupt input	I	External interrupt input pins and always in an input state. Also available as input ports.
P10~P17	I/O	I/O	General purpose I/O pins. Input/output can be specified for each bit.
P30~P37 P40~P47 P50~P57 P60~P67 P70~P77	I/O	I/O	General purpose I/O pins. Input/output can be specified for each port, with 8 bits in one.

## Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).  
Consult our sales staff in advance for information on the following applications:
  - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
  - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
  - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.