



CSMS0610D Series SMD WIRE WOUND POWER INDUCTORS (SHIELDED)


Rev. A

A. Electrical Specifications:

P/N	Marking	Inductance @100KHz (μH)	Inductance Tolerance	DCR ±30%(Ω)	Rated Current (mA)		SRF Min. (MHz)
					I sat	I rms	
CSMS0610D-1R5M	1R5	1.5	± 20%	0.090	2400	1900	77
CSMS0610D-2R2M	2R2	2.2	± 20%	0.110	1900	1700	56
CSMS0610D-3R3M	3R3	3.3	± 20%	0.135	1600	1500	42
CSMS0610D-4R7M	4R7	4.7	± 20%	0.165	1300	1400	36
CSMS0610D-6R8M	6R8	6.8	± 20%	0.220	1200	1200	30
CSMS0610D-100M	100	10	± 20%	0.270	1000	1100	25
CSMS0610D-220M	220	22	± 20%	0.580	650	700	12

B. Dimensions: mm (Inch)

Series	a	b	c	d	e	f	g	h	i	k	m	n
CSMS0610D	6.0 (0.236)	6.0 (0.236)	1.0 (0.039)	1.35 (0.053)	2.3 (0.091)	4.0 (0.157)	4.8 (0.189)	0.3 (0.012)	1.6 (0.063)	5.2 (0.205)	5.7 (0.224)	4.7 (0.185)
Tol.	±0.2 (0.008)	±0.2 (0.008)	Max.	±0.2 (0.008)	Typ.	±0.2 (0.008)	Typ.	Typ.	Typ.	Typ.	Typ.	Typ.



C. General Information:

1. CSMS0610D-xxx_, "CSMS0610D" = P/N, "xxx" = Inductance, "_" = Tolerance.
2. Tolerance "_": M: ± 20%, N: ± 30%
3. Magnetically shielded
4. High saturation current
5. Storage temperature: -40°C to +85°C.
6. Operating temperature range: -25°C to +125°C (Including self-heating).
7. Inductance measured using the HP4285A and Chromal320 & 3302.
8. DCR measured using Chroma 16502.
9. SRF measured using the HP4291B.
10. Saturation Current Idc1: The value of current causes a 30% Inductance reduction from initial value. (at : 20 °C ambient)
11. Temperature rise current Idc2: The value of current causes a 40°C temperature rise. (at : 20 °C ambient)
12. Rated Current: Either Idc1 or Idc2 whichever is smaller.
13. MSL: Level 1.
14. Inductance and Current range: From 1.5 μH (1900mA) to 22.0 μH (650mA).

D. Applications:

1. Game Consoles
2. Set Top Boxes
3. Cables Modems
4. Computers
5. Mobile Communication Devices (Cell Phones, Radios, etc.)
6. PDA, LCD, DVD, BRP, HD.




CSMS0610D Series SMD WIRE WOUND POWER INDUCTORS (SHIELDED)

Rev. A

E. Characteristics Curve:

Inductance vs. Frequency



Inductance vs. DC Current

