120W, AC/DC DIN-Rail mounting





#### **FEATURES**

- Input voltage range: 85 305VAC/100 430VDC
- AC and DC dual-use (input from the same terminal)
- Low standby power consumption, high efficiency, Isolation voltage: 3K VAC
- Low ripple & noise
- Output short circuit, over-current, over-voltage protection
- Remote control
- Active PFC

LI120-13Bxx series — The converter offered by Mornsun. It features Cost-effective, standard rail mounting, energy efficient. It offers stability and high noise immunity for industrial control equipment, machinery and other harsh environments of industrial equipment. The converter is compact size, light weight, compact structure, standard rail (35mm) Installation and save a lot of space for customers.

Selection Guide				
Part No.	Output Power	Nominal Output Voltage and Current (Vo/Io)	Efficiency (230VAC, %/Typ.)	Max. Capacitive Load (µF)
LI120-13B12	120W	12V/10A	89	10000
LI120-13B24	120W	24V/5A	91	4700

Input Specifications						
Item	Operating Condit	ons	Min.	Тур.	Max.	Unit
Input Voltage Range	AC input	AC input			305	VAC
input voltage kange	DC input	DC input			430	VDC
Input frequency			47		63	Hz
In	115VAC		_		1.5	
Input current	230VAC		_		0.75	
	115VAC	LI120-13B12	_	45		Α
Inrush current		LI120-13B24	_	50		
	230VAC		_	70		
Power factor	230VAC	230VAC		≥	0.95	
Hot Plug				Unav	ailable	

Output Specifications							
Item	Operating Conditions		Min.	Тур.	Max.	Unit	
Output Voltage Accuracy				±2			
Line Regulation	Full load			±0.5		%	
Load Regulation	230VAC		-	±1			
0.4.4.5.4.0.1.4	20MHz bandwidth (peak-peak value)	LI120-13B12			100	mV	
Output Ripple & Noise*		LI120-13B24			200		
Temperature Drift Coefficient				±0.03	-	%/°C	
Stand-by Power Consumption					0.75	W	
Short Circuit Protection				Continuous, self-recovery			
O and a summer to Death and the second	LI120-13B12 110 - 150% Io, start protecting aft self-recovery		•	ter 3 seconds,			
Over-current Protection	LI120-13B24		110 - 200% Io, start protecting after 3 seconds, self-recovery			3 seconds,	
Over-voltage Protection			Continuous automatic restart until the over-voltage condition is removed				

**MORNSUN®** 

MORNSUN GUANGZHOU SCIENCE & TECHNOLOGY CO.,LTD.

# AC/DC Converter

#### LI120-13Bxx Series

Switching Frequency

**Power Derating** 

Safety Class

MTBF



100

MIL-HDBK-217F@25°C > 300,000 h

2.5

CLASS I

kHz

%/℃

Min. Load		0		-	%
Start-up Time				3000	
Hold-up Time	230VAC		25		ms
Note: * Rely test method is adopted test the ripple and noise, please see AC-DC Converter Application Notes for specific operation methods.					


General Specit	fications					
Item		Operating Conditions	Min.	Тур.	Max.	Unit
	Input-output	Test time: 1min,Leakage current<5mA	3000			VAC
Isolation Voltage	Input - <del> </del>		1500			
	Output -		500			
Operating Temperature			-25		+70	°C
Storage Temperature			-25		+85	°C
Storage Humidity					95	%RH


Physical Specif	ications	
Casing Material		Heat-resistant plastic (UL94V-0) and metal
Package Dimensions		35.00*125.00*112.70 mm
	LI120-13B12	580g (Typ.)
Weight LI120-13B24		560g (Typ.)
Cooling method		Free air convection

+55℃ to +70℃

EMC Specification	ns			
EN 41	CE	CISPR32/EN55032	CLASS B	
EMI	RE	CISPR32/EN55032	CLASS B	
	ESD	IEC/EN61000-4-2	Contact ±6KV/Air ±8KV	Perf. Criteria B
	RS	IEC/EN61000-4-3	10V/m	perf. Criteria A
	EFT	IEC/EN61000-4-4	±4KV	perf. Criteria B
EMS	Surge	IEC/EN61000-4-5	line to line ±2KV/line to ground ±4KV	perf. Criteria B
	cs	IEC/EN61000-4-6	10Vr.m.s	perf. Criteria A
	Voltage dips, short interruptions and voltage variations immunity	IEC/EN61000-4-11	0%.70%	perf. Criteria B

### **Product Characteristic Curve**







Note:  $\bigcirc$ Input voltage should be derated based on temperature derating when it is 85-100VAC/100-120VDC;

②This product is suitable for use in natural air cooling environments, if in a closed environment, please contact our company's FAE.

**MORNSUN®** 

MORNSUN GUANGZHOU SCIENCE & TECHNOLOGY CO.,LTD.





#### Design Reference

#### 1. Typical application circuit




Fig. 1: Typical application circuit






Fig. 2: Remote control Applications circuit
\*Note: external voltage single range 4.5 - 12.5VDC realize the power off, the single disappears and recovery

2. For more information Please find the application notes on www.mornsun-power.com

#### Dimensions and Recommended Layout





Pin-Out				
Pin	Function			
1	+Vo			
2	+Vo			
3	-Vo			
4	-Vo			
5	AC(N)			
6	AC(L)			

THIRD ANGLE PROJECTION

Note:
Unit: mm[inch]
ADJ: adjustable resistance to change output voltage
Wire range: 26-10 AWG
Tightening torque: Max 0.4 N·m
Mounting rail: TS35, rail needs to connect safety ground

**MORNSUN®** 



#### Notes:

- 1. Packing information please refer to Product Packing Information which can be downloaded from <a href="https://www.mornsun-power.com">www.mornsun-power.com</a>. Packing bag number: 58220028;
- 2. If the product is not operated within the required load range, the product performance cannot be guaranteed to comply with all parameters in the datasheet;
- 3. Unless otherwise specified, parameters in this datasheet were measured under the conditions of Ta=25 °C, humidity<75% with nominal input voltage and rated output load;
- 4. All index testing methods in this datasheet are based on our Company's corporate standards;
- 5. We can provide product customization service, please contact our technicians directly for specific information;
- 6. Products are related to laws and regulations: see "Features" and "EMC";
- 7. Our products shall be classified according to ISO14001 and related environmental laws and regulations, and shall be handled by aualified units.

## Mornsun Guangzhou Science & Technology Co., Ltd.

**MORNSUN®** 

MORNSUN GUANGZHOU SCIENCE & TECHNOLOGY CO.,LTD.