

TOSHIBA Photocoupler GaAlAs Ired & Photo-Triac

TLP665GF

- Office Machine
- Household Use Equipment
- Triac Driver
- Solid State Relay


The TOSHIBA TLP665GF consists of a photo-triac optically coupled to a gallium arsenide infrared emitting diode in a six lead plastic DIP. All parameters are tested to the specification of TLP665G. (both condition and limits)

- Peak off-state voltage: 400V (min.)
- Trigger LED current: 10mA (max.)
- On-state current: 100mA (max.)
- UL recognized: UL1577, file no. E67349
- Isolation voltage: 5000 V_{rms} (min.)
- Option (D4) type
 - VDE approved: DIN VDE0884 / 08.87,
Certificate no.68383
 - Maximum operating insulation voltage: 630V_{PK}
 - Highest permissible over voltage: 6000V_{PK}

(Note 1) When a VDE0884 approved type is needed, please designate the " Option (D4) "

- Structural parameter
 - Creepage distance: 8.0mm (min.)
 - Clearance: 8.0mm (min.)
 - Insulation thickness: 0.5mm (min.)
- Conforming Safety Standards:
 - DIN 57 804 / VDE0804 / 1.83
 - DIN IEC65 / VDE0860 / 8.81
 - DIN IEC380 / VDE0806 / 8.81
 - DIN IEC435 / VDE0805 / Draft Nov. 84
 - DIN IEC601T1 / VDE0750T1 / 5.82
 - BS7002: 1989 (EN60950)


Unit in mm



TOSHIBA 11-9A202

Weight: 0.44 g

Pin Configurations (top view)



- 1 : Anode
- 2 : Cathode
- 3 : NC
- 4 : Terminal 1
- 6 : Terminal 2

RESTRICTIONS ON PRODUCT USE

000707EAA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.