



Description:
This package contains six inverters.

Mode of operation:
All six inverters can be used independently of one another.
For each inverter, a low input gives a high output and vice versa.
The 7414 contains six inverters with Schmitt-trigger inputs and has the same pinout.

Application:
Logical inversion, pulse shaping, oscillators

Data:									
Propagation delay	ns	10	6	2.75	3.5	6	33	9.5	3
Supply current	mA	12	2	8	6.9	26	1.2	3	23
Families:		Std	ALS	AS	F	H	L	LS	S
		●	●	●	●	●	●	●	●

Hex INVERTER

7404