


SILICON BRIDGE RECTIFIERS

3 AMP TO 6 AMPS

TYPE NO.	AVERAGE CURRENT		VOLTAGE	SURGE	VFM	IR
	IO (AV)	@ TA	PIV	IFSM	@ 25C	@ PRV
	(A)	(C)	(V)	(A PK)	(V)	(uA)

SB3 Series 3 AMP Plastic Case SB3 Package



SB305	3.0	50	50	60	1.1 @ 1.5A	10
SB310	3.0	50	100	60	1.1 @ 1.5A	10
SB320	3.0	50	200	60	1.1 @ 1.5A	10
SB340	3.0	50	400	60	1.1 @ 1.5A	10
SB360	3.0	50	600	60	1.1 @ 1.5A	10
SB380	3.0	50	800	60	1.1 @ 1.5A	10
SB3100	3.0	50	1000	60	1.1 @ 1.5A	10

KBL Series 4 AMP Plastic Case KBL Package



KBL401	3.0	50	50	200	1.1 @ 2A	10
KBL402	3.0	50	100	200	1.1 @ 2A	10
KBL403	3.0	50	200	200	1.1 @ 2A	10
KBL404	3.0	50	400	200	1.1 @ 2A	10
KBL405	3.0	50	600	200	1.1 @ 2A	10
KBL406	3.0	50	800	200	1.1 @ 2A	10
KBL407	3.0	50	1000	200	1.1 @ 2A	10

KBU4 Series 4 AMP Plastic Case KBU Package



KBU401	4.0	50	50	200	1.1 @ 2A	10
KBU402	4.0	50	100	200	1.1 @ 2A	10
KBU403	4.0	50	200	200	1.1 @ 2A	10
KBU404	4.0	50	400	200	1.1 @ 2A	10
KBU405	4.0	50	600	200	1.1 @ 2A	10
KBU406	4.0	50	800	200	1.1 @ 2A	10
KBU407	4.0	50	1000	200	1.1 @ 2A	10

SB6 Series 6 AMP Plastic Case SB6 Package



SB601	6.0	50	50	200	1.1 @ 3A	10
SB602	6.0	50	100	200	1.1 @ 3A	10
SB603	6.0	50	200	200	1.1 @ 3A	10
SB604	6.0	50	400	200	1.1 @ 3A	10
SB605	6.0	50	600	200	1.1 @ 3A	10
SB606	6.0	50	800	200	1.1 @ 3A	10
SB607	6.0	50	1000	200	1.1 @ 3A	10

