

ELECTRICAL SPECIFICATIONS:

1.0 TURNS RATIO: (P6-P4-P3) : (J3-J6) : 1CT : 1CT ± 3% (P8-P5-P7) : (J1-J2) : 1CT : 1CT ± 3%

2.0 INDUCTANCE: (P8-P7)

(P8-P7) (P3-P6)

: 350uH MIN. @ 0.1V, 100KHz, 8mA DC Bias

3.0 LEAKAGE INDUCTANCE: P6-P3 (WITH J6 AND J3 SHORT) : 0.35uH MAX. @ 1MHz P8-P7 (WITH J2 AND J1 SHORT) : 0.35uH MAX. @ 1MHz

4.0 INTERWINDING CAPACITANCE: (P6,P4,P3) TO (J6,J3) : 35pf MAX @ 1MHz (P8,P5,P7) TO (J2,J1) : 35pf MAX. @ 1MHZ

5.0 DC RESISTANCE: (J1-J2)

(J3-J6)

: 0.8 ohms Max.

: 1.4 ohms Max.

Bel Stewart Connector 11118 Susquehanna Trail, South Glen Rock, Pa 17327-9199

717.234.7512

NOTES

1.0 PINS WITHOUT ELECTRICAL CONNECTION ARE OMITTED.

MagJack

http://www.stewartconnector.com

EWART SHEET 1 OF 4

: 350uH MIN. @ 0.1V, 100KHz, 8mA DC Bias

DRAWING NO.

SI-50198 REV. 02

THIS DRAWING AND THE SUBJECT MATTER SHOWN THEREON ARE CONFIDENTIAL AND PROPERTY OF BEL STEWART CONNECTOR AND SHALL NOT BE REPRODUCED, COPIED, OR USED IN ANY MANNER WITHOUT PRIOR WRITTEN CONTENT OF BEL STEWART CONNECTOR. THE SUBJECT MATTER MAY BE PATENTED OR A PATENT MAY BE PENDING.

RECEIVE

6.0 RETURN LOSS: (P6-P3)=100 OHMS AND (P8-P7)=100 OHM REF.

© 30MHz
 © 60MHz
 E 13dB MIN.
 © 80MHz
 E 12dB MIN.
 © 100MHz
 E 10dB MIN.

NOTE: 100 OHMS CONNECTED TO (J2-J1) OR (J6-J3).

7.0 DIELECTRIC WITHSTAND: (J1, J2) TO (P8, P7) : 1500 VAC

(J3, J6) TO (P3, P6) : 1500 VAC

8.0 INSERTION LOSS: RS=RL=100 ohms

100KHz TO 100MHz : 1.1 dB TYP

9.0 RISE TIME: RS=100 OHMS AND RL = 100 OHMS

OUTPUT VOLTAGE = 1 V peak : 3.0 nS MAX PULSE WIDTH= 112nS : 3.0 nS MAX

10.0 CROSS TALK: 1-100 MHz : 30 dB TYP


11.0 COMMON TO COMMON MODE ATTENUATION: 1MHz TO 100MHz : 35dB TYP

Bel Stewart Connector 11118 Susquehanna Trail, South Glen Rock, Pa 17327-9199

717.234.7512

MagJack*

http://www.stewartconnector.com



LED SPECIFICATION			
STANDARD LED	WAVELENGTH	* Forward V (MAX)	(TYP)
GREEN	565 nm	2.5 V	2.1 V
YELLOW	590 nm	2.5 V	2.1 V

*WITH A FORWARD CURRENT OF 20 mA

50 MICRO-INCHES MIN. IN CONTACT AREA.

- 2. PIN NOT ELECTRICALLY CONNECTED MAYBE OMITTED. SEE ELECTRICAL DRAWING FOR OMITTED PINS.
- 3. TOLERANCES COMPLY WITH F.C.C. DIMENSION REQUIREMENTS.
- 4. ALL TOLERANCES NOT OTHERWISE SPECIFIED TO BE ±.005 [0.13]
- 5. WAVE SOLDER COMPATIBLE PREHEAT 125°C/90SECS.
 HIGH TEMPERATURE REFLOW COMPATABLE 230°C/90 SEC MAX.

Bel Stewart Connector 11118 Susquehanna Trail, South Glen Rock, Pa 17327-9199 MagJack


http://www.stewartconnector.com


THIS DRAWING AND THE SUBJECT MATTER SHOWN THEREON ARE CONFIDENTIAL AND PROPERTY OF BEL STEWART CONNECTOR AND SHALL NOT BE REPRODUCED, COPIED, OR USED IN ANY MANNER WITHOUT PRIOR WRITTEN CONTENT OF BEL STEWART CONNECTOR. THE SUBJECT MATTER MAY BE PATENTED OR A PATENT MAY BE PENDING.

SHEET DRAWING NO.

717.234.7512

SI-50198 REV.07





- 1. THE SUGGESTED PANEL OPENING IS INTENDED TO GIVE THE USER THE ABILITY TO HAVE REASONABLE JACK / PANEL CLEARANCES YET MAINTAIN RELIABLE GROUNDING CAPABILITY.
- 2. ALL TOLERANCES NOT OTHERWISE SPECIFIED TO BE ±.005 [0.13]

Bel Stewart Connector 11118 Susquehanna Trail, South Glen Rock, Pa 17327-9199 MagJack^e

http://www.stewartconnector.com

SHEET 4 OF 4

717.234.7512

DRAWING NO.

SI-50198 REV. 07