

## ST3243

# 3 to 5.5V, 400Kbps, RS-232 Transceiver with auto-powerdown

#### **General features**

- 1µA supply current achieved when in autopowerdown
- 250kbps minimum guaranteed data rate
- Guaranteed 6V/µs slew rate range
- Guaranteed mouse drive ability
- 0.1µF external capacitors
- Meet EIA/TIA-232 specifications down to 3V
- Available in SO-28, SSOP-28 and TSSOP28


#### Description

The ST3243 device consists of 3 drivers, 5 receivers and a dual charge-pump circuit. The device meets the requirements of EIA/TIA and V.28/V.24 communication standards providing high data rate capability.

The receiver R2 is always active to implement a wake-up feature for serial port.

The ST3243 has a proprietary low-dropout transmitter output stage enabling true RS-232 performance from a 3.0V to 5.5V supply with a dual charge pump. The device is guaranteed to run at data rates of 250kbps while maintaining RS-232 output levels.

<u>The Auto-powerdown feature functions when</u> FORCEON is low and FORCEOFF is high. During this mode of operation, if the device does not



sense a valid RS-232 signal, the driver outputs are disabled. If FORCEOFF is set low, both drivers and receivers (expert R2B) are shut off, and supply current is reduced to 1mA. Disconnecting the serial port or turning off the peripheral drives causes the auto-powerdown condition to occur.

Auto-powerdown can be disabled when FORCEON and FORCEOFF are high, and should be done when driving a serial mouse. With Autopowerdown enabled, the device is activated automatically when a valid signal is applied to any receiver input.

Typical application are in notebook, subnotebook, palmtop computers, battery-powered equipment, hand-held equipment, peripherals and printers.

#### Order code

Part number	Temperature range	Package	Comments
ST3243CDR	0 to 70 °C	SO-28 (Tape & Reel)	1000 parts per reel
ST3243CPR	0 to 70 °C	SSOP-28 (Tape & Reel)	1350 parts per reel
ST3243CTR	0 to 70 °C	TSSOP28 (Tape & Reel)	2500 parts per reel
ST3243BTR	-40 to 85 °C	TSSOP28 (Tape & Reel)	2500 parts per reel

March 2006

### Contents

1	Pin configuration	3
	1.1 Truth tables	4
2	Maximum ratings	5
3	Electrical characteristics	6
4	Application circuits	9
5	Typical performance characteristics	10
6	Package mechanical data 1	12
7	Revision history	20



### 1 Pin configuration

		_
C <sub>2+</sub> [	1 28	] c <sub>1+</sub>
	2 27	] V+
V- [	3 26	□ v <sub>cc</sub>
R1 <sub>IN</sub> [	4 25	] GND
R2 <sub>IN</sub> [	5 24	] C <sub>1-</sub>
R3 <sub>IN</sub> [	6 23	] FORCEON
R4 <sub>IN</sub> [	7 22	FORCEOFF
R5 <sub>IN</sub> [	8 21	I INVALID
Т1 <sub>оит</sub> [	9 20	R2 <sub>outb</sub>
Т2 <sub>оит</sub> [	10 19	R1 <sub>out</sub>
ТЗ <sub>оит</sub> [	11 18	] R2 <sub>out</sub>
T3 <sub>IN</sub> [	12 17	] R3 <sub>out</sub>
T2 <sub>IN</sub> [	13 16	R4 <sub>out</sub>
T1 <sub>IN</sub> [	14 15	] R5 <sub>out</sub>
	CS02110	]

#### Table 1. Pin description

Pin n°	Symbol	Name and function
1	C <sub>2</sub> +	Positive terminal of inverting charge pump capacitor
2	C <sub>2</sub> -	Negative terminal of inverting charge pump capacitor
3	V-	-5.5V Generated by the charge pump
4	R1 <sub>IN</sub>	First receiver input voltage
5	R2 <sub>IN</sub>	Second receiver input voltage
6	R3 <sub>IN</sub>	Third receiver input voltage
7	R4 <sub>IN</sub>	Fourth receiver input voltage
8	R5 <sub>IN</sub>	Fifth receiver input voltage
9	T1 <sub>OUT</sub>	First transmitter output voltage
10	T2 <sub>OUT</sub>	Second transmitter output voltage
11	T3 <sub>OUT</sub>	Third transmitter output voltage
12	T3 <sub>IN</sub>	Third transmitter input voltage
13	T2 <sub>IN</sub>	Second transmitter input voltage
14	T1 <sub>IN</sub>	First transmitter input voltage
15	R5 <sub>OUT</sub>	Fifth receiver output voltage
16	R4 <sub>OUT</sub>	Fourth receiver output voltage
17	R3 <sub>OUT</sub>	Third receiver output voltage



	description	
Pin n°	Symbol	Name and function
18	R2 <sub>OUT</sub>	Second receiver output voltage
19	R1 <sub>OUT</sub>	First receiver output voltage
20	R2 <sub>OUTB</sub>	Non-inverting complementary receiver output, always active for wake-up
21	INVALID	Output of the valid signal detector. Indicates if a valid RS-232 level is present on receiver inputs logic "1"
22	FORCEOFF	Drive low to shut down transmitters and on-board power supply. This over- rides all automatic circuitry and FORCEON
23	FORCEON	Drive high to override automatic circuitry keeping transmitters on (FORCEOFF must be high)
24	C <sub>1</sub> -	Negative terminal of voltage-charge pump capacitor
25	GND	Ground
26	V <sub>CC</sub>	Supply voltage
27	V+	5.5V Generated by the charge pump
28	C <sub>1</sub> +	Positive terminal of voltage-charge pump capacitor

Table 1. Pin description

### 1.1 Truth table

#### Table 2.

FORCE OFF	т <sub>оит</sub>	R <sub>OUT</sub>	R <sub>2OUTB</sub>
0	HIGH Z	HIGH Z	ACTIVE Note:
1	ACTIVE Note:	ACTIVE Note:	ACTIVE Note:

Note: If the part is in auto-powerdown mode (FORCE OFF = VCC, FORCE ON = GND) it is shutdown, if no valid RS-232 levels are present on all receiver input

### 2 Maximum ratings

Symbol	Parameter	Value	Unit
V <sub>CC</sub>	Supply voltage	-0.3 to 6	V
V+	Doubled voltage terminal	(V <sub>CC</sub> -0.3) to 7	V
V-	Inverted voltage terminal	0.3 to -7	V
V+ + V-		13	V
FORCEON, FORCEOFF, T <sub>IN</sub>	Input voltage	-0.3 to 6	V
R <sub>IN</sub>	Receiver input voltage range	± 25	V
T <sub>OUT</sub>	Transmitter output voltage range	± 13.2	V
R <sub>OUT</sub> R <sub>OUTB</sub> INVALID	Receiver output voltage range	-0.3 to (V <sub>CC</sub> + 0.3)	V
t <sub>SHORT</sub>	Short circuit duration on T <sub>OUT</sub> (one at a time)	Continuous	
T <sub>stg</sub>	Storage temperature range	-65 to 150	°C

Table 3. Absolute maximum ratings

Note: 1 Absolute Maximum Ratings are those values beyond which damage to the device may occur. Functional operation under these condition is not implied. V+ and V- can have a maximum magnitude of +7V, but their absolute addition can not exceed 13 V.

2 The device doesn't meet 1KV ESD HBM

### **3** Electrical characteristics

Typical values are referred to  $T_A = 25^{\circ}C$ 

#### Table 4. Electrical characteristics

(C<sub>1</sub> - C<sub>4</sub> = 0.1 $\mu$ F, V<sub>CC</sub> = 3V to 5.5V, T<sub>A</sub> = -40 to 85°C, unless otherwise specified.

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
I <sub>ASHDN</sub>	Supply current auto-powerdown	$V_{CC} = 3.3 \text{ or } 5.0V, T_A = 25^{\circ}C$ All R_IN open, FORCEOFF = $V_{CC}$		1	10	μΑ
I <sub>SHDN</sub>	Shutdown supply current	$V_{CC} = 3.3 \text{ or } 5.0V, T_{A} = 25^{\circ}C$ All R_IN open, FORCEOFF = GND		1	10	μΑ
I <sub>SHDN</sub>	Supply current auto-powerdown disabled	$V_{CC} = 3.3 \text{ or } 5.0 \text{V}$ $T_{A} = 25^{\circ}\text{C}$ FORCEON = FORCEOFF = $V_{CC}$ No Load		0.3	1	mA

#### Table 5. Logic input electrical characteristics

 $(C_1 - C_4 = 0.1 \mu F, V_{CC} = 3V \text{ to } 5.5V, T_A = -40 \text{ to } 85^{\circ}C, \text{ unless otherwise specified.}$ 

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
$V_{TIL}$	Input logic threshold low	T-IN, FORCEON, FORCEOFF			0.8	V
V <sub>TIH</sub>	Input logic threshold high	T-IN, FORCEON, $\overline{FORCEOFF}$ V <sub>CC</sub> = 3.3V V <sub>CC</sub> = 5V	2 2.4			V V
V <sub>THYS</sub>	Transmitter input hysteresis			0.5		V
Ι <sub>ΙL</sub>	Input leakage current	T-IN, FORCEON, FORCEOFF		± 0.01	± 1.0	μΑ
I <sub>OL</sub>	Output leakage current	Receiver Disabled		± 0.05	± 10	μΑ
V <sub>OL</sub>	Output voltage low	I <sub>OUT</sub> = 1.6mA			0.4	V
V <sub>OH</sub>	Output voltage high	I <sub>OUT</sub> = -1mA	V <sub>CC</sub> -0.6	V <sub>CC</sub> -0.1		V



Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
V <sub>RITE</sub>	Receiver input threshold to transmitter enabled	Positive threshold Negative threshold	2.7		2.7	V V
V <sub>RITD</sub>	Receiver input threshold to transmitter disabled	1µA Supply Current	-0.3		0.3	V
V <sub>IOL</sub>	INVALID Output voltage LOW				0.4	V
V <sub>IOH</sub>	INVALID Output voltage HIGH		V <sub>CC</sub> -0.6			V
t <sub>WU</sub>	Receiver threshold to transmitter enabled	I <sub>OUT</sub> = 1.6mA		250		ms
t <sub>invh</sub>	Receiver positive or negative threshold to INVALID HIGH	I <sub>OUT</sub> = -1mA		1		ms
t <sub>invL</sub>	Receiver positive or negative threshold to INVALID LOW			30		ms

 Table 6.
 Auto-powerdown electrical characteristics

 $(C_1 - C_4 = 0.1 \mu F, V_{CC} = 3V \text{ to } 5.5V, T_A = -40 \text{ to } 85^{\circ}C, \text{ unless otherwise specified.}$ 

#### Table 7. Transmitter electrical characteristics

$(C_1 - C_4 = 0.1 \mu F, V_{CC} =$	= 3V to 5.5V. T₄ =	-40 to 85°C.	unless otherwise	specified.
	0 A			

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
V <sub>TOUT</sub>	Output voltage swing	All transmitter outputs are loaded with $3K\Omega$ to GND	±5	±5.4		V
R <sub>OUT</sub>	Output Resistance	$V_{CC} = V + = V - = 0V, V_{OUT} = \pm 2V$	300	10M		Ω
I <sub>SC</sub>	Output short circuit current			± 35	± 60	mA
V <sub>OT</sub>	Transmitter output voltage	T1IN = T2IN = GND, T3IN = $V_{CC}$ T3OUT loaded with $3K\Omega$ to GND T1OUT and T2OUT loaded with 2.5mA each	± 5			V

#### Table 8. Receiver electrical characteristics

(C<sub>1</sub> - C<sub>4</sub> = 0.1 $\mu$ F, V<sub>CC</sub> = 3V to 5.5V, T<sub>A</sub> = -40 to 85°C, unless otherwise specified.

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
V <sub>RIN</sub>	Receiver input voltage operating range		-25		25	V
V <sub>RIL</sub>	RS-232 Input threshold low	$T_A = 25^{\circ}C, V_{CC} = 3.3V$ $T_A = 25^{\circ}C, V_{CC} = 5.0V$	0.6 0.8	1.2 1.2		V
V <sub>RIH</sub>	RS-232 Input threshold high	$T_A = 25^{\circ}C, V_{CC} = 3.3V$ $T_A = 25^{\circ}C, V_{CC} = 5.0V$		1.5 1.8	2.4 2.4	V
V <sub>RIHYS</sub>	Input hysteresis			0.5		V
R <sub>RIN</sub>	Input resistance	$T_A = 25^{\circ}C$	3	5	7	KΩ



#### Table 9.


Timing characteristics (C<sub>1</sub> - C<sub>4</sub> = 0.1µF, V<sub>CC</sub> = 3V to 5.5V, T<sub>A</sub> = -40 to 85°C, unless otherwise specified.

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
D <sub>R</sub>	Maximum data rate	$R_L = 3K\Omega$ , $C_L = 1000pF$ one transmitter switching	250	400		Kbps
t <sub>PHL</sub> t <sub>PLH</sub>	Receiver propagation delay	$R_{IN}$ to $R_{OUT}$ , $C_{L}$ = 150pF		0.15		μs
t <sub>T_SKEW</sub>	Transmitter skew			100		ns
t <sub>R_SKEW</sub>	Receiver skew			50		ns
t <sub>INVH</sub>	Receiver positive or negative threshold to INVALID HIGH			1		ms
t <sub>INVL</sub>	Receiver positive or negative threshold to INVALID LOW			30		ms
S <sub>RT</sub>	Transition slew rate	$ \begin{array}{l} T_A = 25^\circ C  R_L = 3K \text{ to } 7K\Omega  V_{CC} = 3.3V \\ \text{measured from +3V to -3V or -3V to +3V} \\ C_L = 150\text{pF to 1000pF} \\ C_L = 150\text{pF to 2500pF} \end{array} $	6 4		30 30	V/μs V/μs

### ST3243

### 4 Application circuits


#### Figure 2. Application circuits



#### Table 10. Capacitance value (µF)

V <sub>cc</sub>	C1	C2	C3	C4	Cbypass
3.0 to 3.6	0.1	0.1	0.1	0.1	0.1
4.5 to 5.5	0.047	0.33	0.33	0.33	0.33
3.0 to 5.5	0.22	1.0	1.0	1.0	0.22
57					9/20


#### **Typical performance characteristics** 5




Unless otherwise specified  $T_i = 25^{\circ}C$ 




Figure 6. Receiver output enable & disable time



### Figure 7. Output current vs output high voltage






### 6 Package mechanical data

In order to meet environmental requirements, ST offers these devices in ECOPACK® packages. These packages have a Lead-free second level interconnect. The category of second level interconnect is marked on the package and on the inner box label, in compliance with JEDEC Standard JESD97. The maximum ratings related to soldering conditions are also marked on the inner box label. ECOPACK is an ST trademark. ECOPACK specifications are available at: www.st.com




DIM.		mm.			inch		
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.	
А			2.65			0.104	
a1	0.1		0.3	0.004		0.012	
b	0.35		0.49	0.014		0.019	
b1	0.23		0.32	0.009		0.012	
С		0.5			0.020		
c1			45°	(typ.)			
D	17.70		18.10	0.697		0.713	
E	10.00		10.65	0.393		0.419	
е		1.27			0.050		
e3		16.51			0.650		
F	7.40		7.60	0.291		0.300	
L	0.50		1.27	0.020		0.050	



### SO-28 MECHANICAL DATA


13/20

	SSOP28 MECHANICAL DATA							
DIM		mm.			inch			
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.		
А			2			0.079		
A1	0.050			0.002				
A2	1.65	1.75	1.85	0.065	0.069	0.073		
b	0.22		0.38	0.009		0.015		
С	0.09		0.25	0.004		0.010		
D	9.9	10.2	10.5	0.390	0.402	0.413		
E	7.4	7.8	8.2	0.291	0.307	0.323		
E1	5	5.3	5.6	0.197	0.209	0.220		
е		0.65 BSC			0.0256 BSC			
К	0°		10°	0°		10°		
L	0.55	0.75	0.95	0.022	0.030	0.037		




		mm.			inch			
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.		
А			1.2			0.047		
A1	0.05		0.15	0.002	0.004	0.006		
A2	0.8	1	1.05	0.031	0.039	0.041		
b	0.19		0.30	0.007		0.012		
С	0.09		0.20	0.004		0.0079		
D	9.6	9.7	9.8	0.378	0.382	0.386		
E	6.2	6.4	6.6	0.244	0.252	0.260		
E1	4.3	4.4	4.48	0.169	0.173	0.176		
е		0.65 BSC			0.0256 BSC			
К	0°		8°	0°		8°		
L	0.45	0.60	0.75	0.018	0.024	0.030		






15/20

	Tape & Reel SO-28 MECHANICAL DATA								
DIM		mm.			inch				
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.			
А			330			12.992			
С	12.8		13.2	0.504		0.519			
D	20.2			0.795					
Ν	60			2.362					
Т			30.4			1.197			
Ao	10.8		11.0	0.425		0.433			
Во	18.2		18.4	0.716		0.724			
Ко	2.9		3.1	0.114		0.122			
Po	3.9		4.1	0.153		0.161			
Р	11.9		12.1	0.468		0.476			




#### 16/20

	Tape & Reel SSOP28 MECHANICAL DATA									
DIM		mm.			inch					
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.				
А			330			12.992				
С	12.8		13.2	0.504		0.519				
D	20.2			0.795						
Ν	60			2.362						
Т			22.4			0.882				
Ao	8.4		8.6	0.331		0.339				
Во	10.7		10.9	0.421		0.429				
Ko	2.9		3.1	0.114		0.122				
Po	3.9		4.1	0.153		0.161				
Р	11.9		12.1	0.468		0.476				



57

	Tape & Reel TSSOP28 MECHANICAL DATA									
DIM		mm.			inch					
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.				
А			330			12.992				
С	12.8		13.2	0.504		0.519				
D	20.2			0.795						
Ν	60			2.362						
Т			22.4			0.882				
Ao	6.8		7	0.268		0.276				
Во	10.1		10.3	0.398		0.406				
Ko	1.7		1.9	0.067		0.075				
Po	3.9		4.1	0.153		0.161				
Р	11.9		12.1	0.468		0.476				



#### \_ . . -\_

### 7 Revision history

Table 11. Revision history

Date	Revision	Changes	
19-Sep-2004	6	Document updating.	
31-Mar-2006	7	Order codes has been updated and new template.	



#### Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZE REPRESENTATIVE OF ST, ST PRODUCTS ARE NOT DESIGNED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS, WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2006 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan -Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

