General Description

It's mainly suitable for battery pack or power management in cell phone, and PDA.

FEATURES

- V_{DSS}=-20V, I_D=-4.5A.
- Drain-Source ON Resistance.
  : $R_{DS(ON)}$=60mΩ(Max.) @ V_{GS}=-4.5V,.I_D=-4.5A
  : $R_{DS(ON)}$=110mΩ(Max.) @ V_{GS}=-2.5V,.I_D=-3.3A
- Super High Dense Cell Design for Extremely Low $R_{DS(ON)}$



DIM	MILLIMETERS
A	2.926 ± 0.05
B	2.80 ± 0.15
B1	1.626 ± 0.05
C	0.15±0.05
D	1.25 MAX
D1	1.10 ± 0.05
D2	0~0.10
E	0.45 ± 0.08
F	0.95 ± 0.05
G	0.40±0.05

TSOP-6

MAXIMUM RATING (Ta=25℃)

CHARACTERISTIC		SYMBOL	RATING	UNIT
Drain-Source Voltage		V_{DSS}	-20	V
Gate-Source Voltage		V_{GSS}	±12	V
Drain Current	DC	I_D*	±4.5	A
	Pulsed	I_{DP}*	±16	
Continuous Source Current		I_S	-1.3	A
Drain Power Dissipation	Ta=25℃	P_D*	2.0	W
	Ta=70℃		1.3	
Maximum Junction Temperature		T_j	150	℃
Storage Temperature Range		T_{stg}	-55～150	℃
Thermal Resistance, Junction to Ambient		R_{thJA}*	62.5	℃/W

* : Surface Mounted on 1"×1" FR4 Board, t≤5sec.

Marking



PIN CONNECTION (TOP VIEW)





ELECTRICAL CHARACTERISTICS (Ta=25℃)

CHARACTERISTIC	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Static						
Drain-Source Breakdown Voltage	BV_{DSS}	I_D=-250㎂, V_{GS}=0V	-20	-	-	V
Drain Cut-off Current	I_{DSS}	V_{GS}=0V, V_{DS}=-20V	-	-	-1	㎂
		V_{GS}=0V, V_{DS}=-16V, Tj=70℃ (Note 3)	-	-	-5	
Gate Threshold Voltage	V_{th}	V_{DS}=V_{GS}, I_D=-250㎂	-0.6	-	-1.3	V
Gate Leakage Current	I_{GSS}	V_{GS}=±12V, V_{DS}=0V	-	-	±100	nA
Drain-Source ON Resistance	$R_{DS(ON)}$	V_{GS}=-4.5V, I_D=-4.5A (Note 2)	-	49	60	mΩ
		V_{GS}=-2.5V, I_D=-3.3A (Note 2)	-	85	110	
Forward Transconductance	g_{fs}	V_{DS}=-5V, I_D=-4.5A (Note 2)	-	7	-	S
Dynamic (Note 3)						
Total Gate Charge	Q_g	V_{DS}=-10V, R_D=2.2Ω, V_{GS}=-4.5V (Fig.1)	-	8.5	-	nC
Gate-Source Charge	Q_{gs}		-	1.8	-	
Gate-Drain Charge	Q_{gd}		-	2.9	-	
Turn-on Delay time	$t_{d(on)}$	V_{DS}=-10V, R_D=2.2Ω, V_{GS}=-4.5V R_G=6Ω (Fig.2)	-	12	-	ns
Turn-on Rise time	t_r		-	32	-	
Turn-off Delay time	$t_{d(off)}$		-	64	-	
Turn-off Fall time	t_f		-	40	-	
Source-Drain Diode Ratings						
Continuous Source Current	I_S	V_{GS} < V_{th} (Note 1)	-	-	-1.3	A
Diode Forward Voltage	V_{SD}	I_S=-4.5A, V_{GS}=0V (Note 2)	-	-	-1.3	V

Note 1) Based on thermal dissipation from junction to ambient while mounted on a 1" × 1" FR4 Board.

Note 2) Pulse test : Pulse width ≤300㎲, Duty Cycle ≤2%

Note 3) Guaranteed by design, not subject to production testing.

I_D - V_{DS}



I_D - V_{GS}



V_{th} - T_j



$R_{DS(ON)}$ - I_D



I_S - V_{SD}



$R_{DS(ON)}$ - T_j



C - V_{DS}



Q_g - V_{GS}



R_{th}



Fig. 1 Gate Charge



Fig. 2 Resistive Load Switching