

# CHENMKO ENTERPRISE CO.,LTD

## CH481KPT

## **SURFACE MOUNT**

SCHOTTKY BARRIER DIODE VOLTAGE 30 Volts CURRENT 0.2 Ampere

#### **APPLICATION**

\* Low power rectification

#### **FEATURE**


- \* Small surface mounting type. (SC-82/SOT-343)
- \* Extremely low forward voltage.
- \* This is a composite component and is ideal for reducing the number of components used.
- \* High reliability


#### CONSTRUCTION


\* Silicon epitaxial planar

### **MARKING**

\* 3R







#### MAXIMUM RATINGES ( At TA = 25°C unless otherwise noted )

RATINGS	SYMBOL	CH481KPT	UNITS
Maximum Recurrent Peak Reverse Voltage	VRRM	30	Volts
Maximum RMS Voltage	VRMS	21	Volts
Maximum DC Blocking Voltage	VDC	30	Volts
Maximum Average Forward Rectified Current	lo	0.2	Amps
Peak Forward Surge Current at 8.3 mSec single half sine-wave	IFSM	1.0	Amps
Typical Junction Capacitance between Terminal (Note 1)	Cı	6.0	pF
Maximum Operating Temperature Range	TJ	+125	°C
Storage Temperature Range	Тѕтс	-40 to +125	°C

#### **ELECTRICAL CHARACTERISTICS** ( At TA = 25°C unless otherwise noted )

CHARACTERISTICS	SYMBOL	CH481KPT	UNITS
Maximum Instantaneous Forward Voltage at Ir(1)= 10mA	VF(1)	0.33	Volts
Maximum Instantaneous Forward Voltage at IF(2)= 200mA	VF(2)	0.50	Volts
Maximum Average Reverse Current at V <sub>R=</sub> 10V	l <sub>R</sub>	30	uAmps

NOTES: 1. Measured at 1.0 MHz and applied reverse voltage of 10.0 volts.

2. ESD sensitive product handling required.

2002-5

## RATING CHARACTERISTIC CURVES ( CH481KPT )

