www.DataSheet4U.com





# FSA1208 Low-Power, Eight-Port, High-Speed Isolation Switch

#### **Features**

Low On Capacitance: 6pF Typical
Low On Resistance: 15Ω Typical

■ Low Power Consumption: 1µA Maximum

■ 10µA Maximum I<sub>CCT</sub> over an Expanded Voltage Range (V<sub>IN</sub>=2.3V, V<sub>CC</sub>=4.3V)

■ Wide -3db Bandwidth: > 400MHz

 Packaged in Space-Saving 20-Lead MLP (2.5x4.5mm)

8kV ESD Rating; >16kV Power/GND ESD Rating

Low C<sub>OFF</sub> Capacitance: 2.5pF Typical

## **Applications**

DIMM DDR Memory

#### **IMPORTANT NOTE:**

For additional performance information, please contact <a href="mailto:analogswitch@fairchildsemi.com">analogswitch@fairchildsemi.com</a>.

### **Description**


The FSA1208 is a low-power, eight-port, high-speed switch. This part is configured as a single-pole, single-throw switch and is optimized for isolating a high-speed source, such as a DDR memory bus. The FSA1208 features an extremely low on capacitance ( $C_{ON}$ ) of 6pF. Superior channel-to-channel crosstalk minimizes interference.

The FSA1208 contains special circuitry on the A & B pins that allows the device to withstand an over-voltage condition. This device is also designed to minimize current consumption even when the control voltage applied to the /OE pin is lower than the supply voltage (V<sub>CC</sub>). Applications include port isolation and switching in DDR memory modules, portable cell phones, PDAs, digital cameras, printers, and notebook computers.

### **Ordering Information**

Part Number	Top Mark	Operating Temperature Range	Package	© Eco Status
FSA1208BQX	F1208	-40 to +85°C	20-Lead, Quad, Molded Leadless Package (MLP), 2.5x4.5mm	Green

For Fairchild's definition of "green" Eco Status, please visit: <a href="http://www.fairchildsemi.com/company/green/rohs\_green.html">http://www.fairchildsemi.com/company/green/rohs\_green.html</a>.







#### **TRADEMARKS**

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

ACEx® Build it Now™ CorePLUS™ CorePOWER™ CROSSVOLT™ CTL TM

Current Transfer Logic™ EcoSPARK® EfficentMax™ EZSWITCH™ \*

Fairchild<sup>®</sup> Fairchild Semiconductor® FACT\_Quiet Series™

FACT® FAST® FastvCore™\_ FlashWriter®\* FPS™ F-PFS™ FRFET®

Global Power Resources Green FPS™

Green FPS™e-Series™ GTO™

IntelliMAX™ ISOPLANAR™ MegaBuck™ MICROCOUPLER™ MicroFET™ MicroPak™

MillerDrive™ MotionMax™ Motion-SPM™ OPTOLOGIC® OPTOPLANAR® PDP SPM™ Power-SPM™ PowerTrench®

Programmable Active Droop™ QFET®

QSTM

Quiet Series™ RapidConfigure™

Saving our world, 1mW at a time™ SmartMax™

SMART START™ SPM®

STEALTH™ SuperFET™ SuperSOT™-3 SuperSOT™-6 SuperSOT™-8 SupreMOS™ SyncFET™

SYSTEM ®

wer TinyBoost™ TinyBuck™ TinyLogic<sup>®</sup>

The Power Franchise®

TINYOPTO\*\* TinyPower™ TinyPWM™ TinyWire™ μSerDes™

UHC Ultra FRFET™ UniFET™ VCX<sup>TM</sup> VisualMax™

\* EZSWITCH™ and FlashWriter® are trademarks of System General Corporation, used under license by Fairchild Semiconductor.

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN, FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

- 1. Life support devices or systems are devices or systems 2. A critical component in any component of a life support, which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	This datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 134