20 STERN AVE. SPRINGFIELD, NEW JERSEY 07081 U.S.A.

SUS


TELEPHONE: (201) 376-2922 (212) 227-6005

FAX: (201) 376-8960

2N4987,90

The General Electric SUS is a silicon planar, monolithic integrated circuit having thyristor electrical characteristics closely approximating those of an "ideal" four layer diode. The device is designed to switch at 8 volts with a 0.02%/°C temperature coefficient. A gate lead is provided to eliminate rate effect, obtain triggering at lower voltages and to obtain transient free wave forms.

Silicon Unilateral Switches are specifically designed and characterized for use in monostable and bistable applications where low cost is of prime importance. These devices are in the low cost, TO-98 plastic package.



Applications Include:

- Ring Counters
- Cross Point Switching
- SCR TriggersFrequency Dividers
- Over-Voltage Sensors


absolute maximum ratings:

(25°C free air) (unless otherwise specified)

Storage Temperature Range	-65 to +150	°C
Junction Temperature Range	-55 to $+125$	°C
Power Dissipation*	300	$\mathbf{m}\mathbf{W}$
Peak Reverse Voltage	-30	Volts
DC Forward Anode Current*	175	mA.
DC Gate Current*†	5	mA
Peak Recurrent Forward Current		
(1% duty cycle, 10 μ sec pulse width, $T_{A} = 100$ °C)	1.0	Amp
Peak Non-Recurrent Forward Current (10 μ sec pulse width, $T_A = 25$ °C)	5.0	Amps


CIRCUIT SYMBOL

EQUIVALENT CIRCUIT



2.5

pF



*Derate linearly to zero at 125°C.

Capacitance (0V., f = 1 MHz)

†This rating applicable only in OFF state. Maximum gate current in conducting state limited by maximum power rating.

electrical characteristics: (25°C) (unless otherwise specified)

STATIC		2N4987				2N4990	1	
		Min.	Typ.	Max.	Min.	Typ.	Max.	
Forward Switching Voltage	V_8	6.0		10.0	7.0		9.0	Volts
Forward Switching Current	I_{s}			500			200	$\mu \mathbf{A}$
Holding Current	I _H			1.5			.75	m/A
Reverse Current	•			Λ 1			0.1	A
$(V_R = -30V, T_A = 25^{\circ}C)$	Į _R			0.1 10.0			10.0	$\mu \mathbf{A}$ $\mu \mathbf{A}$
$(V_R = -30V, T_A = 85^{\circ}C)$	I_R			10.0			10.0	μει
Forward Current (off state)	-			1.0			0.1	$\mu \mathbf{A}$
$(V_F = 5V, T_A = 25^{\circ}C)$	I _B I _B			1.0 10.0			10.0	$\mu \mathbf{A}$
$(V_r = 5V, T_A = 85^{\circ}C)$	18			10.0			10.0	~
Forward Voltage Drop (on state)	$V_{\mathbf{r}}$			1.5			1.5	Volts
$(I_r = 175 \text{ mA})$	V r,			1.0			1.0	7 0105
Temperature Coefficient of Switching Voltage ($T_A = -55^{\circ}\text{C to } + 85^{\circ}\text{C}$)	$\mathbf{T_c}$	±.02			±.02		%/°C	
Venage (11 = -30 0 to +60 0)								
DYNAMIC								
Turn-on Time (See Circuit 1)	ton			1.0			1.0	usec
Turn-off Time (See Circuit 2)	tore			25.0			25.0	μsec
Peak Pulse Voltage (See Circuit 3)	$\mathbf{v}_{\mathbf{o}}$	3.5			3.5			Volts
· can · coo · conego (coo conego o)								_