

# 74AHC74; 74AHCT74

Dual D-type flip-flop with set and reset; positive-edge trigger

Rev. 04 — 7 February 2005

Product data sheet

## 1. General description

The 74AHC74; 74AHCT74 is a high-speed Si-gate CMOS device and is pin compatible with Low-Power Schottky TTL (LSTTL). It is specified in compliance with JEDEC standard No. 7A.

The 74AHC74; 74AHCT74 is a dual positive-edge triggered, D-type flip-flop with individual data (D) inputs, clock (CP) inputs, set ( $\bar{S}D$ ) and reset ( $\bar{R}D$ ) inputs; also complementary Q and  $\bar{Q}$  outputs.

The set and reset are asynchronous active LOW inputs and operate independently of the clock input. Information on the data input is transferred to the Q output on the LOW-to-HIGH transition of the clock pulse. The D inputs must be stable one set-up time prior to the LOW-to-HIGH clock transition for predictable operation.

Schmitt-trigger action in the clock input makes the circuit highly tolerant to slower clock rise and fall times.

## 2. Features

- Balanced propagation delays
- Inputs accept voltages higher than  $V_{CC}$
- Input levels:
  - ◆ CMOS levels: 74AHC74 only
  - ◆ TTL levels: 74AHCT74 only
- ESD protection:
  - ◆ HBM EIA/JESD22-A114-B exceeds 2000 V
  - ◆ MM EIA/JESD22-A115-A exceeds 200 V
- Specified from  $-40^{\circ}C$  to  $+85^{\circ}C$  and from  $-40^{\circ}C$  to  $+125^{\circ}C$

## 3. Quick reference data

Table 1: Quick reference data

$GND = 0 \text{ V}$ ;  $T_{amb} = 25^{\circ}\text{C}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ .

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
<b>Type 74AHC74</b>						
$t_{PHL}, t_{PLH}$	propagation delay					
	nCP to nQ, n $\bar{Q}$	$C_L = 15 \text{ pF}; V_{CC} = 5 \text{ V}$	-	3.7	-	ns
	n $\bar{S}D$ , n $\bar{R}D$ to nQ, n $\bar{Q}$	$C_L = 15 \text{ pF}; V_{CC} = 5 \text{ V}$	-	3.7	-	ns
$f_{max}$	maximum clock pulse frequency		-	170	-	MHz

**PHILIPS**

**Table 1:** Quick reference data ...continued  
 $GND = 0 \text{ V}$ ;  $T_{amb} = 25^\circ\text{C}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ .

Symbol	Parameter	Conditions	Min	Typ	Max	Unit	
$C_I$	input capacitance	$V_I = V_{CC}$ or GND	-	4.0	-	pF	
$C_{PD}$	power dissipation capacitance	$C_L = 50 \text{ pF}$ ; $f_i = 1 \text{ MHz}$	[1][2]	-	12	-	pF
<b>Type 74AHCT74</b>							
$t_{PHL}, t_{PLH}$	propagation delay						
	nCP to nQ, n $\bar{Q}$	$C_L = 15 \text{ pF}$ ; $V_{CC} = 5 \text{ V}$	-	3.3	-	ns	
	n $\bar{S}D$ , n $\bar{R}D$ to nQ, n $\bar{Q}$	$C_L = 15 \text{ pF}$ ; $V_{CC} = 5 \text{ V}$	-	3.7	-	ns	
$f_{max}$	maximum clock pulse frequency		-	160	-	MHz	
$C_I$	input capacitance	$V_I = V_{CC}$ or GND	-	4.0	-	pF	
$C_{PD}$	power dissipation capacitance	$C_L = 50 \text{ pF}$ ; $f_i = 1 \text{ MHz}$	[1][2]	-	16	-	pF

[1]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ):

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \sum (C_L \times V_{CC}^2 \times f_o) \text{ where:}$$

$f_i$  = input frequency in MHz;

$f_o$  = output frequency in MHz;

$C_L$  = output load capacitance in pF;

$V_{CC}$  = supply voltage in V;

N = number of inputs switching;

$\sum (C_L \times V_{CC}^2 \times f_o)$  = sum of outputs.

[2] The condition is  $V_I = GND$  to  $V_{CC}$ .

## 4. Ordering information

**Table 2:** Ordering information

Type number	Package				Version
	Temperature range	Name	Description		
74AHC74D	-40 °C to +125 °C	SO14	plastic small outline package; 14 leads; body width 3.9 mm		SOT108-1
74AHC74PW	-40 °C to +125 °C	TSSOP14	plastic thin shrink small outline package; 14 leads; body width 4.4 mm		SOT402-1
74AHC74BQ	-40 °C to +125 °C	DHVQFN14	plastic dual in-line compatible thermal enhanced very thin quad flat package; no leads; 14 terminals; body 2.5 × 3 × 0.85 mm		SOT762-1
74AHCT74D	-40 °C to +125 °C	SO14	plastic small outline package; 14 leads; body width 3.9 mm		SOT108-1
74AHCT74PW	-40 °C to +125 °C	TSSOP14	plastic thin shrink small outline package; 14 leads; body width 4.4 mm		SOT402-1
74AHCT74BQ	-40 °C to +125 °C	DHVQFN14	plastic dual in-line compatible thermal enhanced very thin quad flat package; no leads; 14 terminals; body 2.5 × 3 × 0.85 mm		SOT762-1

## 5. Functional diagram




Fig 1. Functional diagram




Fig 2. Logic symbol




Fig 3. IEC logic symbol





Fig 4. Logic diagram (one flip-flop)

## 6. Pinning information

### 6.1 Pinning



### 6.2 Pin description

Table 3: Pin description

Symbol	Pin	Description
1RD̄	1	asynchronous reset-direct input (active LOW)
1D	2	data input
1CP	3	clock input (LOW-to-HIGH, edge-triggered)

**Table 3:** Pin description ...continued

Symbol	Pin	Description
1 $\bar{S}D$	4	asynchronous set-direct input (active LOW)
1Q	5	true flip-flop output
1 $\bar{Q}$	6	complement flip-flop output
GND	7	ground (0 V)
2 $\bar{Q}$	8	complement flip-flop output
2Q	9	true flip-flop output
2 $\bar{S}D$	10	asynchronous set-direct input (active LOW)
2CP	11	clock input (LOW-to-HIGH, edge-triggered)
2D	12	data input
2 $\bar{R}D$	13	asynchronous reset-direct input (active LOW)
V <sub>CC</sub>	14	supply voltage

## 7. Functional description

### 7.1 Function table

**Table 4:** Function table [1]

Input				Output			
n $\bar{S}D$	n $\bar{R}D$	nCP	nD	nQ	n $\bar{Q}$	nQ <sub>n+1</sub>	n $\bar{Q}$ <sub>n+1</sub>
L	H	X	X	H	L	L	H
H	L	X	X	L	H	H	L
L	L	X	X	H	H	-	-
H	H	↑	L	-	-	L	H
H	H	↑	H	-	-	H	L

- [1] H = HIGH voltage level;  
L = LOW voltage level;  
↑ = LOW-to-HIGH transition;  
Q<sub>n+1</sub> = state after the next LOW-to-HIGH CP transition;  
X = don't care.

## 8. Limiting values

**Table 5:** Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Max	Unit
V <sub>CC</sub>	supply voltage		-0.5	+7.0	V
V <sub>I</sub>	input voltage		-0.5	+7.0	V
I <sub>IK</sub>	input diode current	V <sub>I</sub> < -0.5 V	[1]	-20	mA
I <sub>OK</sub>	output diode current	V <sub>O</sub> < -0.5 V or V <sub>O</sub> > V <sub>CC</sub> + 0.5 V	[1]	±20	mA
I <sub>O</sub>	output source or sink current	V <sub>O</sub> = -0.5 V to V <sub>CC</sub> + 0.5 V	-	±25	mA

**Table 5: Limiting values ...continued**

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Max	Unit
I <sub>CC</sub> , I <sub>GND</sub>	V <sub>CC</sub> or GND current		-	±75	mA
T <sub>stg</sub>	storage temperature		-65	+150	°C
P <sub>tot</sub>	total power dissipation T <sub>amb</sub> = -40 °C to +125 °C	[2]	-	500	mW

[1] The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

[2] For SO14 packages: above 70 °C the value of P<sub>tot</sub> derates linearly with 8 mW/K.

For TSSOP14 packages: above 60 °C the value of P<sub>tot</sub> derates linearly with 5.5 mW/K.

For DHVQFN14 packages: above 60 °C the value of P<sub>tot</sub> derates linearly with 4.5 mW/K.

## 9. Recommended operating conditions

**Table 6: Recommended operating conditions**

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
<b>Type 74AHC74</b>						
V <sub>CC</sub>	supply voltage		2.0	5.0	5.5	V
V <sub>I</sub>	input voltage		0	-	5.5	V
V <sub>O</sub>	output voltage		0	-	V <sub>CC</sub>	V
T <sub>amb</sub>	ambient temperature		-40	+25	+125	°C
t <sub>r</sub> , t <sub>f</sub>	input rise and fall times	V <sub>CC</sub> = 3.3 V ± 0.3 V V <sub>CC</sub> = 5 V ± 0.5 V	-	-	100	ns/V
<b>Type 74AHCT74</b>						
V <sub>CC</sub>	supply voltage		4.5	5.0	5.5	V
V <sub>I</sub>	input voltage		0	-	5.5	V
V <sub>O</sub>	output voltage		0	-	V <sub>CC</sub>	V
T <sub>amb</sub>	ambient temperature		-40	+25	+125	°C
t <sub>r</sub> , t <sub>f</sub>	input rise and fall times	V <sub>CC</sub> = 3.3 V ± 0.3 V	-	-	20	ns/V

## 10. Static characteristics

**Table 7: Static characteristics type 74AHC74**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
<b>T<sub>amb</sub> = 25 °C</b>						
V <sub>IH</sub>	HIGH-level input voltage	V <sub>CC</sub> = 2.0 V	1.5	-	-	V
		V <sub>CC</sub> = 3.0 V	2.1	-	-	V
		V <sub>CC</sub> = 5.5 V	3.85	-	-	V
V <sub>IL</sub>	LOW-level input voltage	V <sub>CC</sub> = 2.0 V	-	-	0.5	V
		V <sub>CC</sub> = 3.0 V	-	-	0.9	V
		V <sub>CC</sub> = 5.5 V	-	-	1.65	V

**Table 7: Static characteristics type 74AHC74 ...continued**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = -50 \mu A; V_{CC} = 2.0 \text{ V}$	1.9	2.0	-	V
		$I_O = -50 \mu A; V_{CC} = 3.0 \text{ V}$	2.9	3.0	-	V
		$I_O = -50 \mu A; V_{CC} = 4.5 \text{ V}$	4.4	4.5	-	V
		$I_O = -4.0 \text{ mA}; V_{CC} = 3.0 \text{ V}$	2.58	-	-	V
		$I_O = -8.0 \text{ mA}; V_{CC} = 4.5 \text{ V}$	3.94	-	-	V
$V_{OL}$	LOW-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = 50 \mu A; V_{CC} = 2.0 \text{ V}$	-	0	0.1	V
		$I_O = 50 \mu A; V_{CC} = 3.0 \text{ V}$	-	0	0.1	V
		$I_O = 50 \mu A; V_{CC} = 4.5 \text{ V}$	-	0	0.1	V
		$I_O = 4 \text{ mA}; V_{CC} = 3.0 \text{ V}$	-	-	0.36	V
		$I_O = 8 \text{ mA}; V_{CC} = 4.5 \text{ V}$	-	-	0.36	V
$I_{LI}$	input leakage current	$V_I = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$	-	-	0.1	$\mu A$
$I_{OZ}$	3-state output OFF-state current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_O = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$	-	-	$\pm 0.25$	$\mu A$
$I_{CC}$	quiescent supply current	$V_I = V_{CC}$ or GND; $I_O = 0 \text{ A}$ ; $V_{CC} = 5.5 \text{ V}$	-	-	2.0	$\mu A$
$C_I$	input capacitance	$V_I = V_{CC}$ or GND	-	3	10	pF
<b><math>T_{amb} = -40 \text{ }^{\circ}\text{C}</math> to <math>+85 \text{ }^{\circ}\text{C}</math></b>						
$V_{IH}$	HIGH-level input voltage	$V_{CC} = 2.0 \text{ V}$	1.5	-	-	V
		$V_{CC} = 3.0 \text{ V}$	2.1	-	-	V
		$V_{CC} = 5.5 \text{ V}$	3.85	-	-	V
$V_{IL}$	LOW-level input voltage	$V_{CC} = 2.0 \text{ V}$	-	-	0.5	V
		$V_{CC} = 3.0 \text{ V}$	-	-	0.9	V
		$V_{CC} = 5.5 \text{ V}$	-	-	1.65	V
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = -50 \mu A; V_{CC} = 2.0 \text{ V}$	1.9	-	-	V
		$I_O = -50 \mu A; V_{CC} = 3.0 \text{ V}$	2.9	-	-	V
		$I_O = -50 \mu A; V_{CC} = 4.5 \text{ V}$	4.4	-	-	V
		$I_O = -4.0 \text{ mA}; V_{CC} = 3.0 \text{ V}$	2.48	-	-	V
		$I_O = -8.0 \text{ mA}; V_{CC} = 4.5 \text{ V}$	3.8	-	-	V
$V_{OL}$	LOW-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = 50 \mu A; V_{CC} = 2.0 \text{ V}$	-	-	0.1	V
		$I_O = 50 \mu A; V_{CC} = 3.0 \text{ V}$	-	-	0.1	V
		$I_O = 50 \mu A; V_{CC} = 4.5 \text{ V}$	-	-	0.1	V
		$I_O = 4 \text{ mA}; V_{CC} = 3.0 \text{ V}$	-	-	0.44	V
		$I_O = 8 \text{ mA}; V_{CC} = 4.5 \text{ V}$	-	-	0.44	V
$I_{LI}$	input leakage current	$V_I = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$	-	-	1.0	$\mu A$
$I_{OZ}$	3-state output OFF-state current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_O = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$	-	-	$\pm 2.5$	$\mu A$

**Table 7: Static characteristics type 74AHC74 ...continued**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
I <sub>CC</sub>	quiescent supply current	V <sub>I</sub> = V <sub>CC</sub> or GND; I <sub>O</sub> = 0 A; V <sub>CC</sub> = 5.5 V	-	-	20	µA
C <sub>I</sub>	input capacitance		-	-	10	pF
<b>T<sub>amb</sub> = -40 °C to +125 °C</b>						
V <sub>IH</sub>	HIGH-level input voltage	V <sub>CC</sub> = 2.0 V V <sub>CC</sub> = 3.0 V V <sub>CC</sub> = 5.5 V	1.5 2.1 3.85	- -	-	V
V <sub>IL</sub>	LOW-level input voltage	V <sub>CC</sub> = 2.0 V V <sub>CC</sub> = 3.0 V V <sub>CC</sub> = 5.5 V	- - -	- -	0.5 0.9 1.65	V
V <sub>OH</sub>	HIGH-level output voltage	V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub> I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 2.0 V I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 3.0 V I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 4.5 V I <sub>O</sub> = -4.0 mA; V <sub>CC</sub> = 3.0 V I <sub>O</sub> = -8.0 mA; V <sub>CC</sub> = 4.5 V	1.9 2.9 4.4 2.40 3.70	- - - -	-	V
V <sub>OL</sub>	LOW-level output voltage	V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub> I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 2.0 V I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 3.0 V I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 4.5 V I <sub>O</sub> = 4 mA; V <sub>CC</sub> = 3.0 V I <sub>O</sub> = 8 mA; V <sub>CC</sub> = 4.5 V	- - - - -	- - - -	0.1 0.1 0.1 0.55 0.55	V
I <sub>LI</sub>	input leakage current	V <sub>I</sub> = V <sub>CC</sub> or GND; V <sub>CC</sub> = 5.5 V	-	-	2.0	µA
I <sub>OZ</sub>	3-state output OFF-state current	V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub> ; V <sub>O</sub> = V <sub>CC</sub> or GND; V <sub>CC</sub> = 5.5 V	-	-	±10.0	µA
I <sub>CC</sub>	quiescent supply current	V <sub>I</sub> = V <sub>CC</sub> or GND; I <sub>O</sub> = 0 A; V <sub>CC</sub> = 5.5 V	-	-	40	µA
C <sub>I</sub>	input capacitance		-	-	10	pF

**Table 8: Static characteristics type 74AHCT74**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
<b>T<sub>amb</sub> = 25 °C</b>						
V <sub>IH</sub>	HIGH-level input voltage	V <sub>CC</sub> = 4.5 V to 5.5 V	2.0	-	-	V
V <sub>IL</sub>	LOW-level input voltage	V <sub>CC</sub> = 4.5 V to 5.5 V	-	-	0.8	V
V <sub>OH</sub>	HIGH-level output voltage	V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub> I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 4.5 V I <sub>O</sub> = -8.0 mA; V <sub>CC</sub> = 4.5 V	4.4 3.94	4.5 -	-	V
V <sub>OL</sub>	LOW-level output voltage	V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub> I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 4.5 V I <sub>O</sub> = 8 mA; V <sub>CC</sub> = 4.5 V	- -	0 -	0.1 0.36	V

**Table 8: Static characteristics type 74AHCT74 ...continued**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit	
$I_{LI}$	input leakage current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_{CC} = 5.5$ V	-	-	0.1	$\mu A$	
$I_{OZ}$	3-state output OFF-state current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_O = V_{CC}$ or GND per input pin; other inputs at $V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 5.5$ V	-	-	$\pm 0.25$	$\mu A$	
$I_{CC}$	quiescent supply current	$V_I = V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 5.5$ V	-	-	2.0	$\mu A$	
$\Delta I_{CC}$	additional quiescent supply current per input pin	$V_I = V_{CC} - 2.1$ V; other inputs at $V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 4.5$ V to 5.5 V	-	-	1.35	mA	
$C_I$	input capacitance		-	3	10	pF	
<b><math>T_{amb} = -40</math> °C to +85 °C</b>							
$V_{IH}$	HIGH-level input voltage	$V_{CC} = 4.5$ V to 5.5 V	2.0	-	-	V	
$V_{IL}$	LOW-level input voltage	$V_{CC} = 4.5$ V to 5.5 V	-	-	0.8	V	
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$					
		$I_O = -50 \mu A$ ; $V_{CC} = 4.5$ V	4.4	-	-	V	
		$I_O = -8.0$ mA; $V_{CC} = 4.5$ V	3.8	-	-	V	
$V_{OL}$	LOW-level output voltage	$V_I = V_{IH}$ or $V_{IL}$					
		$I_O = 50 \mu A$ ; $V_{CC} = 4.5$ V	-	-	0.1	V	
		$I_O = 8$ mA; $V_{CC} = 4.5$ V	-	-	0.44	V	
$I_{LI}$	input leakage current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_{CC} = 5.5$ V	-	-	1.0	$\mu A$	
$I_{OZ}$	3-state output OFF-state current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_O = V_{CC}$ or GND per input pin; other inputs at $V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 5.5$ V	-	-	$\pm 2.5$	$\mu A$	
$I_{CC}$	quiescent supply current	$V_I = V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 5.5$ V	-	-	20	$\mu A$	
$\Delta I_{CC}$	additional quiescent supply current per input pin	$V_I = V_{CC} - 2.1$ V; other inputs at $V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 4.5$ V to 5.5 V	-	-	1.5	mA	
$C_I$	input capacitance		-	-	10	pF	
$C_{PD}$	power dissipation capacitance	$C_L = 50$ pF; $f_i = 1$ MHz	[2] [3]	-	16	-	pF
<b><math>T_{amb} = -40</math> °C to +125 °C</b>							
$V_{IH}$	HIGH-level input voltage	$V_{CC} = 4.5$ V to 5.5 V	2.0	-	-	V	
$V_{IL}$	LOW-level input voltage	$V_{CC} = 4.5$ V to 5.5 V	-	-	0.8	V	
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$					
		$I_O = -50 \mu A$ ; $V_{CC} = 4.5$ V	4.4	-	-	V	
		$I_O = -8.0$ mA; $V_{CC} = 4.5$ V	3.70	-	-	V	
$V_{OL}$	LOW-level output voltage	$V_I = V_{IH}$ or $V_{IL}$					
		$I_O = 50 \mu A$ ; $V_{CC} = 4.5$ V	-	-	0.1	V	
		$I_O = 8$ mA; $V_{CC} = 4.5$ V	-	-	0.55	V	
$I_{LI}$	input leakage current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_{CC} = 5.5$ V	-	-	2.0	$\mu A$	
$I_{OZ}$	3-state output OFF-state current	$V_I = V_{IH}$ or $V_{IL}$ ; $V_O = V_{CC}$ or GND per input pin; other inputs at $V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 5.5$ V	-	-	$\pm 10.0$	$\mu A$	

**Table 8:** Static characteristics type 74AHCT74 ...continued

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
I <sub>CC</sub>	quiescent supply current	V <sub>I</sub> = V <sub>CC</sub> or GND; I <sub>O</sub> = 0 A; V <sub>CC</sub> = 5.5 V	-	-	40	µA
ΔI <sub>CC</sub>	additional quiescent supply current per input pin	V <sub>I</sub> = V <sub>CC</sub> – 2.1 V; other inputs at V <sub>CC</sub> or GND; I <sub>O</sub> = 0 A; V <sub>CC</sub> = 4.5 V to 5.5 V	-	-	1.5	mA
C <sub>I</sub>	input capacitance		-	-	10	pF

## 11. Dynamic characteristics

**Table 9:** Dynamic characteristics type 74AHC74GND = 0 V; t<sub>r</sub> = t<sub>f</sub> ≤ 3.0 ns; see [Figure 9](#).

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
T <sub>amb</sub> = 25 °C [1]						
t <sub>PHL</sub> , t <sub>POL</sub>	propagation delay					
	nCP to nQ, n̄Q	V <sub>CC</sub> = 3.0 V to 3.6 V; see <a href="#">Figure 7</a>				
		C <sub>L</sub> = 15 pF	-	5.2	11.9	ns
		C <sub>L</sub> = 50 pF	-	7.4	15.4	ns
		V <sub>CC</sub> = 4.5 V to 5.5 V; see <a href="#">Figure 7</a>				
		C <sub>L</sub> = 15 pF	-	3.7	7.3	ns
		C <sub>L</sub> = 50 pF	-	5.2	9.3	ns
	n̄SD, n̄RD to nQ, n̄Q	V <sub>CC</sub> = 3.0 V to 3.6 V; see <a href="#">Figure 8</a>				
		C <sub>L</sub> = 15 pF	-	5.4	12.3	ns
		C <sub>L</sub> = 50 pF	-	7.7	15.8	ns
		V <sub>CC</sub> = 4.5 V to 5.5 V; see <a href="#">Figure 8</a>				
		C <sub>L</sub> = 15 pF	-	3.7	7.7	ns
		C <sub>L</sub> = 50 pF	-	5.3	9.7	ns
f <sub>max</sub>	maximum clock pulse frequency	V <sub>CC</sub> = 3.0 V to 3.6 V; see <a href="#">Figure 7</a>				
		C <sub>L</sub> = 15 pF	80	125	-	MHz
		C <sub>L</sub> = 50 pF	50	75	-	MHz
		V <sub>CC</sub> = 4.5 V to 5.5 V; see <a href="#">Figure 7</a>				
		C <sub>L</sub> = 15 pF	130	170	-	MHz
		C <sub>L</sub> = 50 pF	90	115	-	MHz
t <sub>w</sub>	pulse width					
	clock pulse HIGH or LOW	C <sub>L</sub> = 50 pF; see <a href="#">Figure 7</a>				
		V <sub>CC</sub> = 3.0 V to 3.6 V	6.0	-	-	ns
		V <sub>CC</sub> = 4.5 V to 5.5 V	5.0	-	-	ns
	set or reset pulse LOW	C <sub>L</sub> = 50 pF; see <a href="#">Figure 8</a>				
		V <sub>CC</sub> = 3.0 V to 3.6 V	6.0	-	-	ns
		V <sub>CC</sub> = 4.5 V to 5.5 V	5.0	-	-	ns

**Table 9: Dynamic characteristics type 74AHC74 ...continued**  
 $GND = 0 \text{ V}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ ; see [Figure 9](#).

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit	
$t_{rem}$	removal time set or reset	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>					
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	5.0	-	-	ns	
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	3.0	-	-	ns	
$t_{su}$	set-up time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>					
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	6.0	-	-	ns	
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	5.0	-	-	ns	
$t_h$	hold time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>					
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	0.5	-	-	ns	
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	0.5	-	-	ns	
$C_{PD}$	power dissipation capacitance	$C_L = 50 \text{ pF}$ ; $f_i = 1 \text{ MHz}$	[2][3]	-	12	-	pF
<b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +85 \text{ }^{\circ}\text{C}</math></b>							
$t_{PHL}, t_{PLH}$	propagation delay	nCP to nQ, $n\bar{Q}$	$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 7</a>				
				1.0	-	14.0	ns
				1.0	-	17.5	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see <a href="#">Figure 7</a>	$C_L = 15 \text{ pF}$	1.0	-	8.5	ns
				1.0	-	10.5	ns
				1.0	-	14.5	ns
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 8</a>	$C_L = 50 \text{ pF}$	1.0	-	18.0	ns
				1.0	-	9.0	ns
				1.0	-	11.0	ns
$f_{max}$	maximum clock pulse frequency	$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 7</a>	$C_L = 15 \text{ pF}$	45	-	-	MHz
				70	-	-	MHz
				110	-	-	MHz
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see <a href="#">Figure 7</a>	$C_L = 50 \text{ pF}$	75	-	-	MHz
				7.0	-	-	ns
				5.0	-	-	ns
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 8</a>	$C_L = 50 \text{ pF}$	7.0	-	-	ns
				5.0	-	-	ns
$t_w$	pulse width	clock pulse HIGH or LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	7.0	-	-	ns
				5.0	-	-	ns
		set or reset pulse LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>	7.0	-	-	ns
				5.0	-	-	ns

**Table 9: Dynamic characteristics type 74AHC74 ...continued**  
 $GND = 0 \text{ V}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ ; see [Figure 9](#).

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
$t_{rem}$	removal time set or reset	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>				
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	5.0	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	3.0	-	-	ns
$t_{su}$	set-up time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>				
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	7.0	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	5.0	-	-	ns
$t_h$	hold time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>				
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	0.5	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	0.5	-	-	ns
<b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +125 \text{ }^{\circ}\text{C}</math></b>						
$t_{PHL}, t_{PLH}$	propagation delay	$nCP$ to $nQ, n\bar{Q}$				
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 7</a>				
		$C_L = 15 \text{ pF}$	1.0	-	15.0	ns
		$C_L = 50 \text{ pF}$	1.0	-	19.5	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see <a href="#">Figure 7</a>				
		$C_L = 15 \text{ pF}$	1.0	-	9.5	ns
		$C_L = 50 \text{ pF}$	1.0	-	12.0	ns
		$n\bar{SD}, n\bar{RD}$ to $nQ, n\bar{Q}$	$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 8</a>			
		$C_L = 15 \text{ pF}$	1.0	-	15.5	ns
		$C_L = 50 \text{ pF}$	1.0	-	20.0	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see <a href="#">Figure 8</a>				
		$C_L = 15 \text{ pF}$	1.0	-	10.0	ns
		$C_L = 50 \text{ pF}$	1.0	-	12.5	ns
$f_{max}$	maximum clock pulse frequency	$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$ ; see <a href="#">Figure 7</a>				
		$C_L = 15 \text{ pF}$	45	-	-	MHz
		$C_L = 50 \text{ pF}$	70	-	-	MHz
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see <a href="#">Figure 7</a>				
		$C_L = 15 \text{ pF}$	110	-	-	MHz
		$C_L = 50 \text{ pF}$	75	-	-	MHz
$t_w$	pulse width	$clock \text{ pulse HIGH or LOW}$	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>			
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	7.0	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	5.0	-	-	ns
		$set \text{ or } reset \text{ pulse LOW}$	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>			
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	7.0	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	5.0	-	-	ns
		$removal \text{ time set or reset}$	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>			
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	5.0	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	3.0	-	-	ns



**Table 9: Dynamic characteristics type 74AHC74 ...continued**  
*GND = 0 V;  $t_r = t_f \leq 3.0 \text{ ns}$ ; see [Figure 9](#).*

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
$t_{su}$	set-up time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>				
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	7.0	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	5.0	-	-	ns
$t_h$	hold time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>				
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	0.5	-	-	ns
		$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$	0.5	-	-	ns

[1] Typical values are measured at nominal  $V_{CC}$ .

[2]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ):

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \sum (C_L \times V_{CC}^2 \times f_o) \text{ where:}$$

$f_i$  = input frequency in MHz;

$f_o$  = output frequency in MHz;

$C_L$  = output load capacitance in pF;

$V_{CC}$  = supply voltage in V;

N = number of inputs switching;

$\sum (C_L \times V_{CC}^2 \times f_o)$  = sum of outputs.

[3] The condition is  $V_I = \text{GND}$  to  $V_{CC}$ .

**Table 10: Dynamic characteristics type 74AHCT74**

*GND = 0 V;  $t_r = t_f \leq 3.0 \text{ ns}$ ;  $V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see [Figure 9](#)*

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
	$T_{amb} = 25^\circ\text{C}$ [1]					
$t_{PLH}, t_{PLH}$	propagation delay nCP to nQ, $n\bar{Q}$	see <a href="#">Figure 7</a>				
		$C_L = 15 \text{ pF}$	-	3.3	7.8	ns
		$C_L = 50 \text{ pF}$	-	4.8	8.8	ns
	n $\bar{S}D$ , n $\bar{R}D$ to nQ, $n\bar{Q}$	see <a href="#">Figure 8</a>				
		$C_L = 15 \text{ pF}$	-	3.7	10.4	ns
		$C_L = 50 \text{ pF}$	-	5.3	11.4	ns
$f_{max}$	maximum clock pulse frequency	see <a href="#">Figure 7</a>				
		$C_L = 15 \text{ pF}$	100	160	-	MHz
		$C_L = 50 \text{ pF}$	80	140	-	MHz
$t_w$	pulse width clock pulse HIGH or LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
		$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
	set or reset pulse LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
	removal time set or reset	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>	3.5	-	-	ns
$t_{su}$	set-up time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
$t_h$	hold time nD to nCP	see <a href="#">Figure 7</a>	0	-	-	ns
$C_{PD}$	power dissipation capacitance	$C_L = 50 \text{ pF}; f_i = 1 \text{ MHz}$	[2][3]	-	16	pF

**Table 10: Dynamic characteristics type 74AHCT74 ...continued** $GND = 0 \text{ V}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ ;  $V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see [Figure 9](#)

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
<b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +85 \text{ }^{\circ}\text{C}</math></b>						
$t_{PHL}, t_{PLH}$	propagation delay nCP to nQ, n $\bar{Q}$	see <a href="#">Figure 7</a> $C_L = 15 \text{ pF}$ $C_L = 50 \text{ pF}$	1.0	-	9.0	ns
	n $\bar{S}D$ , n $\bar{R}D$ to nQ, n $\bar{Q}$	see <a href="#">Figure 8</a> $C_L = 15 \text{ pF}$ $C_L = 50 \text{ pF}$	1.0	-	12.0	ns
			1.0	-	13.0	ns
$f_{max}$	maximum clock pulse frequency	see <a href="#">Figure 7</a> $C_L = 15 \text{ pF}$ $C_L = 50 \text{ pF}$	80	-	-	MHz
			65	-	-	MHz
$t_W$	pulse width clock pulse HIGH or LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
	set or reset pulse LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
$t_{rem}$	removal time set or reset	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 8</a>	3.5	-	-	ns
$t_{su}$	set-up time nD to nCP	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
$t_h$	hold time nD to nCP	see <a href="#">Figure 7</a>	0	-	-	ns
<b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +125 \text{ }^{\circ}\text{C}</math></b>						
$t_{PHL}, t_{PLH}$	propagation delay nCP to nQ, n $\bar{Q}$	see <a href="#">Figure 7</a> $C_L = 15 \text{ pF}$ $C_L = 50 \text{ pF}$	1.0	-	10.0	ns
	n $\bar{S}D$ , n $\bar{R}D$ to nQ, n $\bar{Q}$	see <a href="#">Figure 8</a> $C_L = 15 \text{ pF}$ $C_L = 50 \text{ pF}$	1.0	-	11.0	ns
			1.0	-	13.0	ns
			1.0	-	14.5	ns
$f_{max}$	maximum clock pulse frequency	see <a href="#">Figure 7</a> $C_L = 15 \text{ pF}$ $C_L = 50 \text{ pF}$	80	-	-	MHz
			65	-	-	MHz
$t_W$	pulse width clock pulse HIGH or LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns
	set or reset pulse LOW	$C_L = 50 \text{ pF}$ ; see <a href="#">Figure 7</a>	5.0	-	-	ns

**Table 10: Dynamic characteristics type 74AHCT74 ...continued**GND = 0 V;  $t_r = t_f \leq 3.0$  ns;  $V_{CC} = 4.5$  V to 5.5 V; see [Figure 9](#)

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
$t_{rem}$	removal time set or reset	$C_L = 50$ pF; see <a href="#">Figure 8</a>	3.5	-	-	ns
$t_{su}$	set-up time nD to nCP	$C_L = 50$ pF; see <a href="#">Figure 7</a>	5.0	-	-	ns
$t_h$	hold time nD to nCP	see <a href="#">Figure 7</a>	0	-	-	ns

[1] Typical values are measured at  $V_{CC} = 5.0$  V.[2]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ):

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \sum (C_L \times V_{CC}^2 \times f_o) \text{ where:}$$


 $f_i$  = input frequency in MHz; $f_o$  = output frequency in MHz; $C_L$  = output load capacitance in pF; $V_{CC}$  = supply voltage in V;


N = number of inputs switching;

$$\sum (C_L \times V_{CC}^2 \times f_o) = \text{sum of outputs.}$$

[3] The condition is  $V_I = \text{GND}$  to  $V_{CC}$ .

## 12. Waveforms






Measurement points are given in [Table 11](#).

$V_{OL}$  and  $V_{OH}$  are typical voltage output drop that occur with the output load.

**Fig 8. The set ( $n\bar{S}D$ ) and reset ( $n\bar{R}D$ ) input to output ( $nQ$ ,  $n\bar{Q}$ ) propagation delays, the set and reset pulse widths and the  $n\bar{R}D$  to  $nCP$  removal time**

**Table 11: Measurement points**

Type	Input	Output
	$V_M$	$V_M$
74AHC74	$0.5 \times V_{CC}$	$0.5 \times V_{CC}$
74AHCT74	1.5 V	$0.5 \times V_{CC}$



For test data see [Table 12](#).

Definitions for test circuit:

$C_L$  = Load capacitance including jig and probe capacitance.

$R_T$  = Termination resistance should be equal to output impedance  $Z_o$  of the pulse generator.

**Fig 9. Load circuitry for switching times**



Table 12: Test data

Type	Input		Load $C_L$	Test $t_{PLH}, t_{PHL}$
	$V_I$	$t_r, t_f$		
74AHC74	$V_{CC}$	$\leq 3.0 \text{ ns}$	50 pF, 15 pF	$t_{PLH}, t_{PHL}$
74AHCT74	3.0 V	$\leq 3.0 \text{ ns}$	50 pF, 15 pF	$t_{PLH}, t_{PHL}$

## 13. Package outline

SO14: plastic small outline package; 14 leads; body width 3.9 mm

SOT108-1




Fig 10. Package outline SOT108-1 (SO14)

TSSOP14: plastic thin shrink small outline package; 14 leads; body width 4.4 mm

SOT402-1




Fig 11. Package outline SOT402-1 (TSSOP14)

DHVQFN14: plastic dual in-line compatible thermal enhanced very thin quad flat package; no leads;  
14 terminals; body 2.5 x 3 x 0.85 mm

SOT762-1




Fig 12. Package outline SOT762-1 (DHVQFN14)



## 14. Revision history

**Table 13: Revision history**

Document ID	Release date	Data sheet status	Change notice	Doc. number	Supersedes
74AHC_AHCT74_4	20050207	Product data sheet	-	9397 750 14504	74AHC_AHCT74_3
Modifications:	<ul style="list-style-type: none"><li>The format of this data sheet is redesigned to comply with the current presentation and information standard of Philips Semiconductors.</li><li>Added: type numbers 74AHC74BQ and 74AHCT74BQ (DHVQFN14 package).</li></ul>				
74AHC_AHCT74_3	20040429	Product specification	-	9397 750 13118	74AHC_AHCT74_2
74AHC_AHCT74_2	19990923	Product specification	-	9397 750 06291	74AHC_AHCT74_1
74AHC_AHCT74_1	19990805	Product specification	-	9397 750 05747	-

## 15. Data sheet status

Level	Data sheet status [1]	Product status [2][3]	Definition
I	Objective data	Development	This data sheet contains data from the objective specification for product development. Philips Semiconductors reserves the right to change the specification in any manner without notice.
II	Preliminary data	Qualification	This data sheet contains data from the preliminary specification. Supplementary data will be published at a later date. Philips Semiconductors reserves the right to change the specification without notice, in order to improve the design and supply the best possible product.
III	Product data	Production	This data sheet contains data from the product specification. Philips Semiconductors reserves the right to make changes at any time in order to improve the design, manufacturing and supply. Relevant changes will be communicated via a Customer Product/Process Change Notification (CPCN).

[1] Please consult the most recently issued data sheet before initiating or completing a design.

[2] The product status of the device(s) described in this data sheet may have changed since this data sheet was published. The latest information is available on the Internet at URL <http://www.semiconductors.philips.com>.

[3] For data sheets describing multiple type numbers, the highest-level product status determines the data sheet status.

## 16. Definitions

**Short-form specification** — The data in a short-form specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.

**Limiting values definition** — Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 60134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

**Application information** — Applications that are described herein for any of these products are for illustrative purposes only. Philips Semiconductors make no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

## 17. Disclaimers

**Life support** — These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips Semiconductors customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips Semiconductors for any damages resulting from such application.

**Right to make changes** — Philips Semiconductors reserves the right to make changes in the products - including circuits, standard cells, and/or software - described or contained herein in order to improve design and/or performance. When the product is in full production (status 'Production'), relevant changes will be communicated via a Customer Product/Process Change Notification (CPCN). Philips Semiconductors assumes no responsibility or liability for the use of any of these products, conveys no license or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

## 18. Contact information

For additional information, please visit: <http://www.semiconductors.philips.com>

For sales office addresses, send an email to: [sales.addresses@www.semiconductors.philips.com](mailto:sales.addresses@www.semiconductors.philips.com)



## 19. Contents

1	General description .....	1
2	Features .....	1
3	Quick reference data .....	1
4	Ordering information .....	2
5	Functional diagram .....	3
6	Pinning information .....	4
6.1	Pinning .....	4
6.2	Pin description .....	4
7	Functional description .....	5
7.1	Function table .....	5
8	Limiting values .....	5
9	Recommended operating conditions .....	6
10	Static characteristics .....	6
11	Dynamic characteristics .....	10
12	Waveforms .....	15
13	Package outline .....	18
14	Revision history .....	21
15	Data sheet status .....	22
16	Definitions .....	22
17	Disclaimers .....	22
18	Contact information .....	22

© Koninklijke Philips Electronics N.V. 2005

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Date of release: 7 February 2005  
Document number: 9397 750 14504



Published in The Netherlands