

## UltraLogic™ Very High Speed 12K (36K) Gate 3.3V ČMOS FPGA

## Features

- Full 3.3V operation
- Very high speed
  - Loadable counter frequencies greater than 100 MHz
  - Chip-to-chip operating frequencies up to 85 MHz
  - Input + logic cell + output delays under 7 ns
- Unparalleled FPGA performance for counters, data path, state machines, arithmetic, and random logic
- High usable density
  - 32 x 28 array of 896 logic cells provides 36,000 total available gates
  - 12.000 typically usable "gate array" gates
- Available in 208-pin POFP and 352-pin BGA
- Fully PCI compliant inputs & outputs
- Low power, high output drive
  - Standby current typically 100 uA
  - 16-bit counter operating at 100 MHz consumes 25 mA
- Flexible logic cell architecture
  - Wide fan-in (up to 14 input gates)
  - Multiple outputs in each cell
  - Very low cell propagation delay (1.4 ns typical)

- Robust routing resources
  - Fully automatic place and route of designs using up to 100 percent of logic resources
  - No hand routing required
- 256 bidirectional input/output pins
- 8 dedicated input/high-drive pins
- 8 fanout-independent, low-skew clock
  - 4 fast clocks driven from dedicated input pins
  - 4 global clocks driven from any pin or internal logic
  - Clock skew < 0.5 ns
- Input registers
  - Set-up time <2 ns
- Input hysteresis provides high noise immunity
- Full JTAG testability
- 0.65µ triple layer metal CMOS process with ViaLink™ programming
  - High-speed metal-to-metal link
  - Non-volatile antifuse technology
- Powerful design tools-Warp3
  - Designs entered in VHDL. schematics, or mixed


- --- Fast, fully automatic place and route
- Waveform simulation with back annotated net delays
- PC and workstation platforms
- Extensive third party tools support
  - See Development Systems section


## **Functional Description**

The Ultra338012 is a very high speed, 3.3V. CMOS, user-programmable ASIC device. The 896 logic cell field-programmable gate array (FPGA) offers 12,000 typically usable "gate array" gates. This is equivalent to 36,000 EPLD or LCA gates. The Ultra338012 is available in a 208-pin PQFP and 352-pin BGA packages.

Low-impedance, metal-to-metal ViaLink interconnect technology provides non-volatile custom logic capable of operating at speeds above 100 MHz with input delays under 4 ns and output delays under 5.5 ns. This permits high-density programmable devices to be used with today's fastest CISC and RISC microprocessors.

For detailed information about the Ultra38000 ™ architecture, Ultra38000 Family datasheet.





ViaLink and pASIC are trademarks of QuickLogic Corporation. Warp3, Ultra38000, and UltraLogic are trademarks of Cypress Semiconductor Corporation.

Document #: 38-00491