




CONDENSED FOR POWER (CFP) TRANSFORMERS


Single 115V or dual 115V/230V, rated 50/60 Hz.
2500 RMS Hipot, Class S (130 degree C) Rated
Special Terminal solder or quick connect.
UL File Number 110331




S E C T	Part Number		VA Size	Secondary RMS Ratings
	115V Primary	115/230V Primary		Series
A	CFP-201	CFP-200	2.4	10V CT @ 250MA
	CFP-301	CFP-300	6	10V CT @ 600MA
	CFP-401	CFP-400	12	10V CT @ 1.2A
	CFP-501	CFP-500	30	10V CT @ 3.0A
	CFP-601	CFP-600	56	10V CT @ 5.0A
	CFP-701	CFP-700	100	10V CT @ 10.0A
B	CFP-203	CFP-202	2.4	12.6V CT @ 200MA
	CFP-303	CFP-302	6	12.6V CT @ 500MA
	CFP-403	CFP-402	12	12.6V CT @ 1.0A
	CFP-503	CFP-502	30	12.6V CT @ 2.5A
	CFP-603	CFP-602	56	12.6V CT @ 4.0A
	CFP-703	CFP-702	100	12.6V CT @ 8.0A
C	CFP-205	CFP-204	2.4	16V CT @ 150MA
	CFP-305	CFP-304	6	16V CT @ 400MA
	CFP-405	CFP-404	12	16V CT @ 800MA
	CFP-505	CFP-504	30	16V CT @ 2.0A
	CFP-605	CFP-604	56	16V CT @ 3.5A
	CFP-705	CFP-704	100	16V CT @ 6.25A
D	CFP-207	CFP-206	2.4	20V CT @ 120MA
	CFP-307	CFP-306	6	20V CT @ 300MA
	CFP-407	CFP-406	12	20V CT @ 600MA
	CFP-507	CFP-506	30	20V CT @ 1.5A
	CFP-607	CFP-606	56	20V CT @ 2.8A
	CFP-707	CFP-706	100	20V CT @ 5.0A
E	CFP-209	CFP-208	2.4	24V CT @ 100MA
	CFP-309	CFP-308	6	24V CT @ 250MA
	CFP-409	CFP-408	12	24V CT @ 500MA
	CFP-509	CFP-508	30	24V CT @ 1.25A
	CFP-609	CFP-608	56	24V CT @ 2.4A
	CFP-709	CFP-708	100	24V CT @ 4.0A
F	CFP-211	CFP-210	2.4	28V CT @ 85MA
	CFP-311	CFP-310	6	28V CT @ 200MA
	CFP-411	CFP-410	12	28V CT @ 420MA
	CFP-511	CFP-510	30	28V CT @ 1.1A
	CFP-611	CFP-610	56	28V CT @ 2.0A
	CFP-711	CFP-710	100	28V CT @ 3.6A
G	CFP-213	CFP-212	2.4	36V CT @ 65MA
	CFP-313	CFP-312	6	36V CT @ 170MA
	CFP-413	CFP-412	12	36V CT @ 350MA
	CFP-513	CFP-512	30	36V CT @ 850MA
	CFP-613	CFP-612	56	36V CT @ 1.5A
	CFP-713	CFP-712	100	36V CT @ 2.8A
H	CFP-215	CFP-214	2.4	48V CT @ 50MA
	CFP-315	CFP-314	6	48V CT @ 125MA
	CFP-415	CFP-414	12	48V CT @ 250MA
	CFP-515	CFP-514	30	48V CT @ 630MA
	CFP-615	CFP-614	56	48V CT @ 1.2A
	CFP-715	CFP-714	100	48V CT @ 2.0A
I	CFP-217	CFP-216	2.4	56V CT @ 45MA
	CFP-317	CFP-316	6	56V CT @ 110MA
	CFP-417	CFP-416	12	56V CT @ 220MA
	CFP-517	CFP-516	30	56V CT @ 540MA
	CFP-617	CFP-616	56	56V CT @ 1.0A
	CFP-717	CFP-716	100	56V CT @ 1.8A
J	CFP-219	CFP-218	2.4	120V CT @ 20MA
	CFP-319	CFP-318	6	120V CT @ 50MA
	CFP-419	CFP-418	12	120V CT @ 100MA
	CFP-519	CFP-518	30	120V CT @ 250MA
	CFP-619	CFP-618	56	120V CT @ 500MA
	CFP-719	CFP-718	100	120V CT @ 850MA



Single 115V




Dual 115/230V



VA Size	Dimensions in inches						Wt. Lbs.
	L	W	H	A	B	MW	
2.4	2 1/8	1 3/16	1 1/4	1 5/8	9/16	1 3/4	.3
6	2 3/8	1 5/16	1 3/8	1 11/16	1 1/16	2	.5
12	2 7/8	1 1/2	1 5/8	1 15/16	1 3/16	2 3/8	.7
30	3 1/4	1 23/32	1 15/16	2 5/16	1 1/16	2 13/16	1.1
56	3 3/4	1 27/32	2 1/4	2 11/16	1 1/16	3 1/8	1.7
100	4	2 1/4	2 9/16	3 1/16	1 5/16	3 9/16	2.8


Dimensions are for reference only, and should not be used for specification purposes.

FOR SINGLE PRIMARY




SIZES 2.4, 6, 12


FOR DUAL PRIMARY



SIZES 2.4, 6, 12



SIZES 30, 56, 100



SIZES 30, 56, 100