



PJSMDA05C SERIES

QUAD TVS/ZENER ARRAY FOR ESD AND LATCH-UP PROTECTION

This Quad TVS/Zener Array family have been designed to Protect Sensitive Equipment against ESD and to prevent Latch-Up events in CMOS circuitry operating at 5V,12V,15V and 24V.

This TVS array offers an integrated solution to protect up to 4 data lines where the board space is a premium.

FEATURES



- 350W Power Dissipation (8/20 μ s Waveform)
- Low Leakage Current, Maximum of 5 μ A at rated voltage
- Very Low Clamping Voltage
- IEC61000-4-2 ESD 20kV air,15kV Contact Compliance
- In compliance with EU RoHS 2002/95/EC directives

MECHANICAL DATA

- Case: SOIC-08,Molded plastic over passivated junction
- Terminals: Solderable per MIL-STD-750, Method 2026
- Approx. Weight: 0.079 grams
- Mounting Position : Any

APPLICATIONS

- RS-232C or RS-422 Communication ports
- GPIB/IEEE 485 Ports
- Portable Instrumentation



MAXIMUM RATINGS (Per Device)

Rating	Symbol	Value	Units
Peak Pulse Power (8/20 μ s Waveform)	P _{PP}	350	W
ESD Voltage (HBM) Per MIL-STD-883C	V _{ESD}	>25	kV
Operating Temperature Range	T _J	-50 to +150	°C
Storage Temperature Range	T _{STG}	-50 to +150	°C



PJSMDA05C SERIES

ELECTRICAL CHARACTERISTICS (PER DEVICE) T_J = 25°C


PJSMDA05C Marking DC5						
Parameter	Symbol	Condition	Min.	Typ.	Max.	Units
Reverse Stand-Off Voltage	V _{RWM}		-	-	5	V
Reverse Breakdown Voltage	V _{BR}	I _{BR} =1mA	6	-	-	V
Reverse Leakage Current	I _R	V _R =5V	-	-	5	μA
Clamping Voltage (8/20μs)	V _C	I _{PP} =5A	-	-	9.8	V
Clamping Voltage (8/20μs)	V _C	I _{PP} =24A	-	-	13	V
Off State Junction Capacitance	C _J	0 Vdc Bias f=1MHz	-	270	300	pF
Off State Junction Capacitance	C _J	5 Vdc Bias f=1MHz	-	200	230	pF
PJSMDA12C Marking DC2						
Parameter	Symbol	Condition	Min.	Typ.	Max.	Units
Reverse Stand-Off Voltage	V _{RWM}		-	-	12	V
Reverse Breakdown Voltage	V _{BR}	I _{BR} =1mA	13.3	-	-	V
Reverse Leakage Current	I _R	V _R =5V	-	-	5	μA
Clamping Voltage (8/20μs)	V _C	I _{PP} =5A	-	-	20	V
Clamping Voltage (8/20μs)	V _C	I _{PP} =15A	-	-	25	V
Off State Junction Capacitance	C _J	0 Vdc Bias f=1MHz	-	-	150	pF
PJSMDA15C Marking DCC						
Parameter	Symbol	Condition	Min.	Typ.	Max.	Units
Reverse Stand-Off Voltage	V _{RWM}		-	-	15	V
Reverse Breakdown Voltage	V _{BR}	I _{BR} =1mA	16.7	-	-	V
Reverse Leakage Current	I _R	V _R =5V	-	-	5	μA
Clamping Voltage (8/20μs)	V _C	I _{PP} =5A	-	-	24	V
Clamping Voltage (8/20μs)	V _C	I _{PP} =12A	-	-	29	V
Off State Junction Capacitance	C _J	0 Vdc Bias f=1MHz	-	-	100	pF
PJSMDA24C Marking DC4						
Parameter	Symbol	Condition	Min.	Typ.	Max.	Units
Reverse Stand-Off Voltage	V _{RWM}		-	-	24	V
Reverse Breakdown Voltage	V _{BR}	I _{BR} =1mA	26.7	-	-	V
Reverse Leakage Current	I _R	V _R =5V	-	-	5	μA
Clamping Voltage (8/20μs)	V _C	I _{PP} =5A	-	-	40	V
Clamping Voltage (8/20μs)	V _C	I _{PP} =8A	-	-	44	V
Off State Junction Capacitance	C _J	0 Vdc Bias f=1MHz	-	-	60	pF




PJSMDA05C SERIES

TYPICAL CHARACTERISTICS $T_J = 25^\circ\text{C}$ unless otherwise noted


Surge Pulse Waveform Definition




Non-Repetitive Peak Pulse Power vs Pulse Time



Clamping Voltage vs. Peak current




Off-State Capacitance per Device - 1MHz





PJSMDA05C SERIES

MOUNTING PAD LAYOUT



ORDER INFORMATION

- Packing information
T/R - 3K per 13" plastic Reel

LEGAL STATEMENT

Copyright PanJit International, Inc 2009

The information presented in this document is believed to be accurate and reliable. The specifications and information herein are subject to change without notice. Pan Jit makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose. Pan Jit products are not authorized for use in life support devices or systems. Pan Jit does not convey any license under its patent rights or rights of others.