

## STPS3150-Y

## Automotive power Schottky rectifier

#### **Features**

- AEC-Q101 qualified
- Negligible switching losses
- Low forward voltage drop for higher efficiency and extented battery life
- Low thermal resistance
- ECOPACK®2 compliant component

### **Description**

Packaged in SMB, this device is intended for use in automotive applications where low drop forward voltage is required to reduce power dissipation.



Table 1. Device summary

Symbol	Value
I <sub>F(AV)</sub>	3 A
$V_{RRM}$	150 V
T <sub>j</sub> (max)	175 °C
V <sub>F</sub> (max)	0.67 V

Characteristics STPS3150-Y

#### 1 Characteristics

Table 2. Absolute ratings (limiting values)

Symbol	Parameter			Unit
$V_{RRM}$	Repetitive peak reverse voltage		150	٧
I <sub>F(AV)</sub>	Average forward current $T_L = 130  ^{\circ}\text{C}  \delta = 0$	0.5	3	Α
I <sub>FSM</sub>	Surge non repetitive forward current $t_p = 10 \text{ ms sinuson}$	idal	80	Α
T <sub>stg</sub>	Storage temperature range		-65 to +175	°C
T <sub>j</sub>	Operating junction temperature range <sup>(1)</sup>		-40 to +175	°C

<sup>1.</sup>  $\frac{dPtot}{dTj} < \frac{1}{Rth(j-a)}$  condition to avoid thermal runaway for a diode on its own heatsink

Table 3. Thermal resistance

Symbol	Parameter	Value	Unit
R <sub>th(j-l)</sub>	Junction to lead	20	°C/W

Table 4. Static electrical characteristics

Symbol	Parameter	Tests conditions		Min.	Тур	Max.	Unit
I <sub>R</sub> <sup>(1)</sup>	Reverse leakage current $\frac{T_j = 25 \text{ °C}}{T_j = 125 \text{ °C}} V_R = V_{RRM}$	V V		0.4	2.0	μΑ	
'R`		T <sub>j</sub> = 125 °C	$v_R = v_{RRM}$		0.6	2.0	mA
		$T_j = 25 ^{\circ}\text{C}$ $T_j = 125 ^{\circ}\text{C}$ $I_F = 3 ^{\circ}\text{A}$		0.78	0.82		
V (2)	/ <sub>F</sub> <sup>(2)</sup> Forward voltage drop			0.63	0.67	V	
VF`'		T <sub>i</sub> = 25 °C	I - 6 A		0.85	0.89	V
		T <sub>j</sub> = 125 °C	I <sub>F</sub> = 6 A		0.70	0.75	


<sup>1.</sup>  $t_p = 5 \text{ ms}, \delta < 2\%$ 


To evaluate the conduction losses use the following equation:

$$P = 0.59 \text{ x } I_{F(AV)} + 0.023 I_{F^2(RMS)}$$

Figure 1. Average forward power dissipation versus average forward current

Figure 2. Average forward current versus ambient temperature ( $\delta$  = 0.5)






<sup>2.</sup>  $t_p = 380 \ \mu s, \ \delta < 2\%$ 

STPS3150-Y Characteristics

Figure 3. Non repetitive surge peak forward current versus overload duration (maximum values)

Figure 4. Normalized avalanche power derating versus pulse duration



PARM(tp)
PARM(1 μs)

0.1


0.01

0.01

1 1 10 100 1000

Figure 5. Normalized avalanche power derating versus junction temperature

Figure 6. Relative variation of thermal impedance junction to ambient versus pulse duration








Figure 7. Reverse leakage current versus reverse voltage applied (typical values)

Figure 8. Junction capacitance versus reverse voltage applied (typical values)






Characteristics STPS3150-Y

Figure 9. Forward voltage drop versus forward current

Figure 10. Forward voltage drop versus forward current







Figure 11. Thermal resistance junction to ambient versus copper surface under each lead




## 2 Package information

- Epoxy meets UL94, V0
- Lead-free package


In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK® packages, depending on their level of environmental compliance. ECOPACK® specifications, grade definitions and product status are available at: <a href="www.st.com">www.st.com</a>. ECOPACK® is an ST trademark.

Table 5. SMB dimensions



	Dimensions				
Ref.	Millimeters		Inc	hes	
	Min.	Max.	Min.	Max.	
A1	1.90	2.45	0.075	0.096	
A2	0.05	0.20	0.002	0.008	
b	1.95	2.20	0.077	0.087	
С	0.15	0.40	0.006	0.016	
Е	5.10	5.60	0.201	0.220	
E1	4.05	4.60	0.159	0.181	
D	3.30	3.95	0.130	0.156	
L	0.75	1.50	0.030	0.059	

Figure 12. SMB footprint (dimensions in mm)



Ordering information STPS3150-Y

# 3 Ordering information

Table 6. Ordering information

Order code	Marking	Package	Weight	Base qty	Delivery mode
STPS3150UY	G315Y	SMB	0.107 g	2500	Tape and reel

# 4 Revision history

Table 7. Document revision history

Date	Revision	Description of Changes
03-Nov-2011	1	Initial release.

#### Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY TWO AUTHORIZED ST REPRESENTATIVES, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2011 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com



# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

STMicroelectronics: STPS3150UY