

**Micro Commercial Components** 

Micro Commercial Components 20736 Marilla Street Chatsworth CA 91311

Phone: (818) 701-4933 Fax: (818) 701-4939

# MMBTA05 THRU MMBTA06

## **Features**

- Epitaxial Planar Die Construction
- Complementary PNP Types Available (MMBTA55/MMBTA56)
- Ideal for Medium Power Amplification and Switching.
- Case Material: Molded Plastic. UL Flammability Classificatio Rating 94-0 and MSL Rating 1
- Marking: MMBTA05:1H/K1H MMBTA06:1GM/K1G

#### **Maximum Ratings**

Symbol	Rating	Rating	Unit
$V_{CEO}$	Collector-Emitter Voltage		
	MMBTA05	60	V
	MMBTA06	80	
$V_{CBO}$	Collector-Base Voltage		
	MMBTA05	60	V
	MMBTA06	80	
$V_{EBO}$	Emitter-Base Voltage	4.0	V
I <sub>C</sub>	Collector Current-Continuous	500	mA
$P_{D}$	Power Dissipation*	300	mW
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	357	K/W
TJ	Operating Junction Temperature	-55 to +150	$^{\circ}$
T <sub>STG</sub>	Storage Temperature	-55 to +150	$^{\circ}\mathbb{C}$

#### Electrical Characteristics @ $25^{\circ}$ C Unless Otherwise Specified


Symbol	Parameter	Min	Max	Units
OFF CHARA	ICTERISTICS			
$V_{(BR)CEO}$	Collector-Emitter Breakdown Voltage (I <sub>C</sub> =1.0mAdc, I <sub>R</sub> =0)			\/- -
	MMBTA05	60		Vdc
	MMBTA06	80		
$V_{(BR)EBO}$	Emitter-Base Breakdown Voltage			
, ,	$(I_E=100\mu Adc, I_C=0)$	4.0		Vdc
I <sub>CBO</sub>	Collector Cutoff Current			
	(V <sub>CB</sub> =60Vdc, I <sub>E</sub> =0) MMBTA05		0.1	μAdc
	(V <sub>CB</sub> =80Vdc, I <sub>E</sub> =0) MMBTA06		0.1	μAdc
I <sub>CES</sub>	Emitter Cutoff Current			
	$(V_{CE}=60Vdc, I_{B}=0)$ MMBTA05		0.1	μAdc
	(V <sub>CE</sub> =80Vdc, I <sub>B</sub> =0) MMBTA06		0.1	µAdc

#### **ON CHARACTERISTICS**


h <sub>FE</sub>	DC Current Gain			
	$(V_{CE}=1.0Vdc, I_{C}=10mAdc)$	100		
	$(V_{CE}=1.0Vdc, I_{C}=100mAdc)$	100		
V <sub>CE(sat)</sub>	Collector-Emitter Saturation Voltage			
	(I <sub>C</sub> =100mAdc, I <sub>B</sub> =10mAdc)		0.25	Vdc
$V_{BE(on)}$	Base-Emitter On Voltage			
. ,	(I <sub>C</sub> =100mAdc, IB=10mAdc)		1.2	Vdc
f⊤	Current-Gain—Bandwidth Product			
	(I <sub>C</sub> =10mAdc, V <sub>CE</sub> =2.0Vdc, f=100MHz)	100		MHz

<sup>\*</sup> Valid provided that terminals are kept at ambient temperature..

# NPN Small Signal General Purpose Amplifier Transistors




DIMENSIONS					
	INCHES		MM		
DIM	MIN	MAX	MIN	MAX	NOTE
Α	.110	.120	2.80	3.04	
В	.083	.098	2.10	2.64	
C	.047	.055	1.20	1.40	
D	.035	.041	.89	1.03	
Е	.070	.081	1.78	2.05	
F	.018	.024	.45	.60	
Ŋ	.0005	.0039	.013	.100	
Η	.035	.044	.89	1.12	
J	.003	.007	.085	.180	
K	.015	.020	.37	.51	








### MMBTA05


#### **Typical Characteristics**



















# **MMBTA06**

# **Typical characteristics**






I<sub>C</sub>. COLLECTOR CURRENT (mA) Fig. 2, Typical Pulsed Current Gain vs. Collector Current



I<sub>B,</sub> BASE CURRENT (mA) Fig. 3 Typical Collector Saturation Region





### Ordering Information

Device	Packing
(Part Number)-TP	Tape&Reel3Kpcs/Reel

#### \*\*\*IMPORTANT NOTICE\*\*\*

Micro Commercial Components Corp. reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes.
Micro Commercial Components Corp. does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Micro Commercial Components Corp. and all the companies whose products are represented on our website, harmless against all damages.

#### \*\*\*APPLICATIONS DISCLAIMER\*\*\*

Products offer by *Micro Commercial Components Corp* . are not intended for use in Medical,

Aerospace or Military Applications.