CARDINAL COMPONENTS

Low Profile Crystals

Cardinal "AT-Strip" low profile crystals come in a variety of heights and specifications to accommodate all of our customers' requirements.



CLP5 CLP6

Part Numbering Example: CLP X - A1 B2 C2 200 - 3.579545 D18 - 3

| CĻP | X | A1* | B2 | C ₂ | 200 | 3.579545 | D18 | - 3 |
|-----------------------------|---|---|-------------------------------------|--|-----|----------|-----|---|
| CLP CLP3 CLP4 CLP5 | ADDED FEATURES F = FORMED LEADS W = VINYL SLEEVING X = INSULATOR PAD Y = THIRD LEAD Z = TAPE AND REEL BLANK = BULK PACK | $A0 = -10^{\circ}\text{C} \sim +60^{\circ}\text{C}$ $A1 = -10^{\circ}\text{C} \sim +70^{\circ}\text{C}$ $A2 = -40^{\circ}\text{C} \sim +85^{\circ}\text{C}$ | B1 = ±100 B2 = ± 50 B3 = ± 30 | $C1 = \pm 100$ $C2 = \pm 50$ $C3 = \pm 30$ | | | | OVERTONE BLANK: FUND3: 3rd OT -5: 5th OT -7: 7th OT -BT: BT Cut |

^{*}NOTE: The above ABC combinations cover basic specification options. We tailor our crystal specifications to meet customer requirements. Please contact our sales department if you don't see exactly what you need.

Specifications:

Frequency Range:

| 3.579 | 9545 ~ 38.000 MHz | AT Cut Fundamental | | |
|-----------------------------|---------------------------|--------------------|--|--|
| 25.000 | AT Cut 3rd Overtone | | | |
| 26.000 | 0000 ~ 42.000 MHz | BT Cut Fundamental | | |
| Operating Temperatur | e: -10°C ~ +70°C | Standard | | |
| | -40°C ~ +85°C | | | |
| Frequency Stability: | ±100 ppm | | | |
| | ± 50 ppm | Standard | | |
| | ± 30 ppm | | | |
| | ± 15 ppm | | | |
| Frequency Tolerance: | ±100 ppm | | | |
| (at 25°C) | ± 50 ppm | Standard | | |
| | ± 30 ppm | | | |
| | ± 10 ppm | | | |
| Load Capacitance: | Standard 18 pF or series. | | | |

Please specify your required load.

Resistance: Maximum resistance corresponds to frequency.

See chart below.

Standard: Mode: Fundamental or 3rd Overtone

Shunt Capacitance: 7 pF Max

Aging: ± 5 ppm/year Drive Level: 1.0 mW Max

Formed Leads **Optional Features:**

> Vinyl Sleeves Insulator Pads Radial Tape and Reel


Note 1: Not all combinations of the above tolerances, stabilities, and temperature ranges are available. Consult the factory if your requirement is not standard.

Heights of 3.5 mm (0.138) and 2.5 mm (0.098) are also available. Please consult factory if required.


Resistance Chart: All resistances are maximum values.


| EQUIVALENT SERIES RESISTANCE (ESR), MODE OF OPERATION (MODE), AND CUT | | | | | | | | | |
|---|---------------|----------|---------------|-----------------|-----------------|--|--|--|--|
| Frequency MHz | $ESR(\Omega)$ | Mode/cut | Frequency MHz | ESR (Ω) | Mode/cut | | | | |
| 3.579545~4.999 | 200 Max | Fund./AT | 15.000~15.999 | 60 Max | Fund./AT | | | | |
| 5.000~5.999 | 150 Max | Fund./AT | 16.000~23.999 | 50 Max | Fund./AT | | | | |
| 6.000~7.999 | 120 Max | Fund./AT | 24.000~30.000 | 40 Max | Fund./AT | | | | |
| 8.000~8.999 | 90 Max | Fund./AT | 24.000~48.000 | 40 Max | Fund./BT | | | | |
| 9.000~9.999 | 80 Max | Fund./AT | 24.576~29.999 | 150 Max | 3rd Overtone/AT | | | | |
| 10.000~14.999 | 70 Max | Fund./AT | 30.000~75.000 | 100 Max | 3rd Overtone/AT | | | | |

CLP



CLP3







Cardinal Components, Inc., 155 Rt. 46 W, Wayne, NJ. 07470 TEL: (973) 785-1333 FAX: (973) 785-0053 E-Mail: cardinal@cardinalxtal.com http://www.cardinalxtal.com