# 2.5V / 3.3Vdc PROGRAMMABLE SPREAD SPECTRUM LOW EMI CLOCK OSCILLATOR



7.0 x 5.0 x 1.4mm

#### **FEATURES**:

- Spread Spectrum LOW EMI Oscillator
- 7.0 x 5.0 x 1.4mm Ceramic package
- Tri-state function
- Suitable for RoHS reflow profile

**ASSVP SERIES** 

• Seam sealed ceramic package assures high reliability.

# > STANDARD SPECIFICATIONS:

## > APPLICATIONS:

- Laptop computerPDA
  - Mot
- LCD
- Digital camera
- Wireless LANMobile phone

(Pb

- Printer
  - Flat TV

Quick Turn Delivery! <5 Days for small quantities!

RoHS

Compliant

PARAMETERS	
ABRACON P/N	ASSVP Series
Frequency range:	10.00000MHz - 160.00000MHz
Spread type (Typical):	Center Spread: ±0.125% to ±2.00% Down Spread: -0.25% to -4.00% (see Table 3 for options)
EMI reduction	-7dBc min. 100MHz at C02
(Reduction is applied to the entire	-9dBc min. 100MHz at C04
frequency spectrum)	-12dBc min. 100MHz at C12 With respect to the dB level when no modulation.
Operating temperature:	-40°C to + 85°C
Storage temperature:	-55°C to + 125°C
Frequency stability:	±50ppm (see options) *
Supply voltage (Vdd):	2.5, or 3.3 V ± 10% (see options)
Start-up time:	2ms typ. 10ms max.
Rise time / fall time	See table 1 or 2 below
Load:	15pF (30pF max)
Current consumption:	See table 1 or 2 below
Duty cycle:	50% ± 5% (C <sub>L</sub> = 15pF at 50% V <sub>DD</sub> )
Output type:	CMOS
Aging (First year)	±3ppm max.; Ta=+25°C
Output Voltage "High" ; "1":	90% V <sub>DD</sub> min.
Output Voltage "Low" ; "0":	10% V <sub>DD</sub> max.
Modulation carrier frequency (Dither rate):	Programmable dependant ( 30kHz to 40kHz )
Tri-state function :	Logic "1" or open: Oscillation
	Logic "0" (VIL < 0.8 Vdc) : Hi Z

\* Frequency stability includes initial tolerance, temperature characteristics, load variation, and supply voltage variation,.


Tabl	<u>م</u>	1.	2	5\/
ומט ו	e	ι.	۷.	ЭV.

	Current consumption (mA)		Tr/Tf (nsec)	
Frequency	Typical	Max	Typical	Max
10 to 49.99MHz	10	20	2.0	5.0
50 to 79.99MHz	15	20	2.0	4.0
80 to 99.99MHz	20	25	1.5	3.0
100 to 160MHz	25	30	1.5	3.0

#### Table 2: 3.3V

	Current consumption (mA)		Tr/Tf (nsec)	
Frequency	Typical	Max	Typical	Max
10 to 49.99MHz	15	20	3.0	10.0
50 to 79.99MHz	20	25	2.5	8.0
80 to 99.99MHz	25	30	2.0	5.0
100 to 160MHz	30	40	1.5	4.0






## Table 3: SPREAD SPECTRUM BANDWIDTH SELECTION TABLE

SPREAD SPECTRUM BAND WIDTH OPTIONS					
Center Sp	Center Spread (%)		Down Spread (%)		
C01	±0.125	D01	-0.25		
C02	±0.250	D02	-0.50		
C03	±0.375	D03	-0.75		
C04	±0.50	D04	-1.00		
C05	±0.625	D05	-1.25		
C06	±0.750	D06	-1.50		
C07	±0.875	D07	-1.75		
C08	±1.000	D08	-2.00		
C09	±1.125	D09	-2.25		
C10	±1.250	D10	-2.50		
C11	±1.375	D11	-2.75		
C12	±1.500	D12	-3.00		
C13	±1.625	D13	-3.25		
C14	±1.750	D14	-3.50		
C15	±1.875	D15	-3.75		
C16	±2.000	D16	-4.00		







Need a test socket for the ASSVP Series? To view compatible **PRECISION TEST and BURN-IN SOCKETS** for these parts, **click here.**  **ATTENTION:** Abracon Corporation's products are COTS – Commercial-Off-The-Shelf products; suitable for Commercial, Industrial and, where designated, Automotive Applications. Abracon's products are not specifically designed for Military, Aviation, Aerospace, Life-dependant Medical applications or any application requiring high reliability where component failure could result in loss of life and/or property. For applications requiring high reliability and/or presenting an extreme operating environment, written consent and authorization from Abracon Corporation is required. Please contact Abracon Corporation for more information.

ABRACON IS ISO9001:2008 CERTIFIED



Visit www.abracon.com for Terms & Conditions of Sale **Revised: 10.12.10** 30332 Esperanza, Rancho Santa Margarita, California 92688 tel 949-546-8000 | fax 949-546-8001 | www.abracon.com